PLC-XU350

XGA Ultraportable Multimedia Projector



COMPLETE EASY AUTO SET UP FUNCTION, SMART AUTO INPUT SEARCH AND AUTO VERTICAL KEYSTONE CORRECTION

PLC-XU350 provides "Auto Set Up Function" that corrects keystone shaped distortion by searching for an input signal and detecting projector incline, therefore reducing set up time. PLC-XU350 automatically compensates for keystone picture distortion. Auto Keystone Correction, Auto Input Search and Auto PC Adjustment make it a really smart projector.

NETWORKING CAPABILITY

Bright 3500Im, the PLC-XU350 is equipped with SANYO's exclusive PJ-Net Master Network Interface software for wired and wireless networking, a common feature among SANYO's extensive line of commercial projectors. Networking allows the monitoring of projector functions and operation from a long distance via a web browser for up 15,000 Sanyo projectors. Emails can be sent automatically to report operating status.

SHORT THROW LENS WITH 1.2 ZOOM AND 1W SPEAKER

PLC-XU350 is equipped with a zoom lens that allows screen size adjustment. The optical zoom works to maintain the image quality. The short-focus type lens allows large screen image projections with a short throw distance. The PLC-XU350 enables 100-inch screen projection at the shortest distance, 83 inches. Along with its mobility, the PLC-XU350 features a high-output 1 Watt speaker. Sufficient audio is delivered through its built-in speaker, so the projector can be used in small conference rooms, classrooms, and other similar spaces.

BLACK BOARD / COLOR BOARD MODE

What could be more right for education? A black board mode. The PLC-XU350 is compatible with four colored (red, blue, green and yellow) projection surfaces via the 'Color Board Mode'. It adjusts the color to make images look as true as on an ordinary white screen.

LAMP REPLACEMENT ON TOP CABINET

There is access to the lamp from the top of the projector which means you can replace the lamp on a ceiling-mounted unit without taking down the projector.

CLOSED CAPTION

PLC-XU350 Closed Caption compatible.





PRESENTATION TECHNOLOGIES

21605 Plummer Street Chatsworth, CA 91311 Ph: 888-337-1215 (toll-free) Fax 818.717.2719 www.sanyoprojectors.com

Specifications

		CITICATIONS
Resolution		XGA (1,024 x 768)
Brightness (typical)		3500
Uniformity		85%
Panel System		0.63" TFT Polyx3
Number of Pixels		2,359.296 (786,432 x3)
Contrast Ratio (Full on / off)		500:1
Image Size		40"-300"
Aspect Ratio		4:3
Projection Lamp (s)		225W UHP
Scanning Frequen	•	H:15-100kHZ V:50-100Hz
Dot Clock		140MHz
Fan Noise		29dBA(Eco) 34dBA(Normal)
Voltage		100-240V
BTU Rating		1,126 (Normal) 860W(Eco)
Power Consumption		330W (Normal) 252W(Eco)
rower consumption		UXGA / WXGA / SXGA+ / SXGA / XGA / SVGA / VGA /
Input signal compatibility		
		MAC, 480i / 480p / 575i / 575p / 720p / 1080i NTSC / PAL / SECAM / NTSC4.43 / PAL-M / PAL-N
Color System Projection Lens (inch)		F1.65 – 1.76 f=0.88" - 1.06"
Throw Ratio		1.74 - 2.09
Throw Distance (feet)		4.6' - 41.7'
Zoom / Focus		Manual
Zoom Ratio		1:1.2
Up / Down Ratio		9:1
Digital Keystone Correction		V +/- 30° (Auto Keystone)
Projection System		Diachronic mirror & X prism system w/PBS
Digital Zoom		16x - 1/4x
Speaker Output		1W
Weight (lbs.)		5.7lbs.
Dimensions (inch) W,H,D		12.8"x3.3x9.1
Replacement Lamp		645 099 3213
Replacement Rem	note	610 343 2069
	DC1	Dsub-15 x 1 (RGB, Component, Scart RGB)
	DC1	Doub 15 x 1 (NOD, Component, Scart NOD)
1	PC1	
		Mini jack x 1 (Audio input, stereo) Dsub-15 x 1 (in common)
Input	PC1	Mini jack x 1 (Audio input, stereo) Dsub-15 x 1 (in common)
Input		Mini jack x 1 (Audio input, stereo) Dsub-15 x 1 (in common) Mini jack x 1 (Audio input, stereo)
Input	PC2	Mini jack x 1 (Audio input, stereo) Dsub-15 x 1 (in common) Mini jack x 1 (Audio input, stereo) Mini DIN 4-pin x 1 (S-Video)
Input		Mini jack x 1 (Audio input, stereo) Dsub-15 x 1 (in common) Mini jack x 1 (Audio input, stereo) Mini DIN 4-pin x 1 (S-Video) RCA x 1 (Composite Video)
	PC2	Mini jack x 1 (Audio input, stereo) Dsub-15 x 1 (in common) Mini jack x 1 (Audio input, stereo) Mini DIN 4-pin x 1 (S-Video) RCA x 1 (Composite Video) RCA x 2 (Audio input, R/ L-mono)
Input Out Put	PC2	Mini jack x 1 (Audio input, stereo) Dsub-15 x 1 (in common) Mini jack x 1 (Audio input, stereo) Mini DIN 4-pin x 1 (S-Video) RCA x 1 (Composite Video) RCA x 2 (Audio input, R/ L-mono) Dsub-15 x 1 (in common)
	PC2	Mini jack x 1 (Audio input, stereo) Dsub-15 x 1 (in common) Mini jack x 1 (Audio input, stereo) Mini DIN 4-pin x 1 (S-Video) RCA x 1 (Composite Video) RCA x 2 (Audio input, R/ L-mono) Dsub-15 x 1 (in common) Mini jack x 1 (Audio out, stereo variable)
	PC2	Mini jack x 1 (Audio input, stereo) Dsub-15 x 1 (in common) Mini jack x 1 (Audio input, stereo) Mini DIN 4-pin x 1 (S-Video) RCA x 1 (Composite Video) RCA x 2 (Audio input, R/ L-mono) Dsub-15 x 1 (in common) Mini jack x 1 (Audio out, stereo variable) Dsub-9 x 1 (Control port)
Out Put	PC2	Mini jack x 1 (Audio input, stereo) Dsub-15 x 1 (in common) Mini jack x 1 (Audio input, stereo) Mini DIN 4-pin x 1 (S-Video) RCA x 1 (Composite Video) RCA x 2 (Audio input, R/ L-mono) Dsub-15 x 1 (in common) Mini jack x 1 (Audio out, stereo variable) Dsub-9 x 1 (Control port) USB-B x 1 (Mouse control)
Out Put	PC2	Mini jack x 1 (Audio input, stereo) Dsub-15 x 1 (in common) Mini jack x 1 (Audio input, stereo) Mini DIN 4-pin x 1 (S-Video) RCA x 1 (Composite Video) RCA x 2 (Audio input, R/ L-mono) Dsub-15 x 1 (in common) Mini jack x 1 (Audio out, stereo variable) Dsub-9 x 1 (Control port) USB-B x 1 (Mouse control) RJ-45 x 1 (Wired LAN)
Out Put Control 1	PC2	Mini jack x 1 (Audio input, stereo) Dsub-15 x 1 (in common) Mini jack x 1 (Audio input, stereo) Mini DIN 4-pin x 1 (S-Video) RCA x 1 (Composite Video) RCA x 2 (Audio input, R/ L-mono) Dsub-15 x 1 (in common) Mini jack x 1 (Audio out, stereo variable) Dsub-9 x 1 (Control port) USB-B x 1 (Mouse control) RJ-45 x 1 (Wired LAN) USB-A x 1 (Memory viewer)
Out Put Control 1	PC2	Mini jack x 1 (Audio input, stereo) Dsub-15 x 1 (in common) Mini jack x 1 (Audio input, stereo) Mini DIN 4-pin x 1 (S-Video) RCA x 1 (Composite Video) RCA x 2 (Audio input, R/ L-mono) Dsub-15 x 1 (in common) Mini jack x 1 (Audio out, stereo variable) Dsub-9 x 1 (Control port) USB-B x 1 (Mouse control) RJ-45 x 1 (Wired LAN) USB-A x 1 (Memory viewer) Quick reference guide, CD-ROM read me note, UL cable
Out Put Control 1 Others	PC2 VIDEO	Mini jack x 1 (Audio input, stereo) Dsub-15 x 1 (in common) Mini jack x 1 (Audio input, stereo) Mini DIN 4-pin x 1 (S-Video) RCA x 1 (Composite Video) RCA x 2 (Audio input, R/ L-mono) Dsub-15 x 1 (in common) Mini jack x 1 (Audio out, stereo variable) Dsub-9 x 1 (Control port) USB-B x 1 (Mouse control) RJ-45 x 1 (Wired LAN) USB-A x 1 (Memory viewer) Quick reference guide, CD-ROM read me note, UL cable card, PIN code label, Computer cable, Power cord, Remote
Out Put Control 1	PC2 VIDEO	Mini jack x 1 (Audio input, stereo) Dsub-15 x 1 (in common) Mini jack x 1 (Audio input, stereo) Mini DIN 4-pin x 1 (S-Video) RCA x 1 (Composite Video) RCA x 2 (Audio input, R/ L-mono) Dsub-15 x 1 (in common) Mini jack x 1 (Audio out, stereo variable) Dsub-9 x 1 (Control port) USB-B x 1 (Mouse control) RJ-45 x 1 (Wired LAN) USB-A x 1 (Memory viewer) Quick reference guide, CD-ROM read me note, UL cable card, PIN code label, Computer cable, Power cord, Remote control, AAA Battery x 2, User's manual (CD ROM), Network
Out Put Control 1 Others	PC2 VIDEO	Mini jack x 1 (Audio input, stereo) Dsub-15 x 1 (in common) Mini jack x 1 (Audio input, stereo) Mini DIN 4-pin x 1 (S-Video) RCA x 1 (Composite Video) RCA x 2 (Audio input, R/ L-mono) Dsub-15 x 1 (in common) Mini jack x 1 (Audio out, stereo variable) Dsub-9 x 1 (Control port) USB-B x 1 (Mouse control) RJ-45 x 1 (Wired LAN) USB-A x 1 (Memory viewer) Quick reference guide, CD-ROM read me note, UL cable card, PIN code label, Computer cable, Power cord, Remote control, AAA Battery x 2, User's manual (CD ROM), Network PJ-Net Manager software (CD ROM), Soft carrying case,
Out Put Control 1 Others Included Accessor	PC2 VIDEO	Mini jack x 1 (Audio input, stereo) Dsub-15 x 1 (in common) Mini jack x 1 (Audio input, stereo) Mini DIN 4-pin x 1 (S-Video) RCA x 1 (Composite Video) RCA x 2 (Audio input, R/ L-mono) Dsub-15 x 1 (in common) Mini jack x 1 (Audio out, stereo variable) Dsub-9 x 1 (Control port) USB-B x 1 (Mouse control) RJ-45 x 1 (Wired LAN) USB-A x 1 (Memory viewer) Ouick reference guide, CD-ROM read me note, UL cable card, PIN code label, Computer cable, Power cord, Remote control, AAA Battery x 2, User's manual (CD ROM), Network PJ-Net Manager software (CD ROM), Soft carrying case, Strap for Lens cap
Out Put Control 1 Others Included Accessor Optional Accessor	PC2 VIDEO	Mini jack x 1 (Audio input, stereo) Dsub-15 x 1 (in common) Mini jack x 1 (Audio input, stereo) Mini DIN 4-pin x 1 (S-Video) RCA x 1 (Composite Video) RCA x 2 (Audio input, R/ L-mono) Dsub-15 x 1 (in common) Mini jack x 1 (Audio out, stereo variable) Dsub-9 x 1 (Control port) USB-B x 1 (Mouse control) RJ-45 x 1 (Wired LAN) USB-A x 1 (Memory viewer) Quick reference guide, CD-ROM read me note, UL cable card, PIN code label, Computer cable, Power cord, Remote control, AAA Battery x 2, User's manual (CD ROM), Network PJ-Net Manager software (CD ROM), Soft carrying case, Strap for Lens cap
Out Put Control 1 Others Included Accessor	PC2 VIDEO	Mini jack x 1 (Audio input, stereo) Dsub-15 x 1 (in common) Mini jack x 1 (Audio input, stereo) Mini DIN 4-pin x 1 (S-Video) RCA x 1 (Composite Video) RCA x 2 (Audio input, R/ L-mono) Dsub-15 x 1 (in common) Mini jack x 1 (Audio out, stereo variable) Dsub-9 x 1 (Control port) USB-B x 1 (Mouse control) RJ-45 x 1 (Wired LAN) USB-A x 1 (Memory viewer) Quick reference guide, CD-ROM read me note, UL cable card, PIN code label, Computer cable, Power cord, Remote control, AAA Battery x 2, User's manual (CD ROM), Network PJ-Net Manager software (CD ROM), Soft carrying case, Strap for Lens cap POA-CACOMPVGA-Component Video Cable Clean air filters, replace lamp assembly
Out Put Control 1 Others Included Accessor Optional Accessor	PC2 VIDEO	Mini jack x 1 (Audio input, stereo) Dsub-15 x 1 (in common) Mini jack x 1 (Audio input, stereo) Mini DIN 4-pin x 1 (S-Video) RCA x 1 (Composite Video) RCA x 2 (Audio input, R/ L-mono) Dsub-15 x 1 (in common) Mini jack x 1 (Audio out, stereo variable) Dsub-9 x 1 (Control port) USB-B x 1 (Mouse control) RJ-45 x 1 (Wired LAN) USB-A x 1 (Memory viewer) Quick reference guide, CD-ROM read me note, UL cable card, PIN code label, Computer cable, Power cord, Remote control, AAA Battery x 2, User's manual (CD ROM), Network PJ-Net Manager software (CD ROM), Soft carrying case, Strap for Lens cap

Because its products are subject to continuous improvement, SANYO reserves the right to modify product design and specifications without notice and without incurring any obligations.



Rear Back Panel

Issued 3/09 ©2009 SANYO