

SONIFEX

Redbox RB-UL4 & RB-LU4

Quad Converters

June 2012

catalogue



Manufacturers of audio & video products
for radio & TV broadcasters

RB-UL4 Quad Stereo Unbalanced To Balanced Converter



Audio Specification For RB-UL4

Maximum Input Level:	+28dBu
Maximum Output Level:	+28dBu
Input Impedance:	>10kΩ
Output Impedance:	<50Ω
Distortion:	0.01% THD @ 1kHz, ref +8dBu output
Noise:	-100dB, unity gain, ref +8dBu output
Frequency Response:	20Hz to 20kHz ±0.1dB (600Ω load, ref 1kHz)
Gain Range:	Balanced output: -15dBu to +15dBu, ref -15dBu into unbalanced RCA input

Connections

Inputs:	8 x RCA phono (Unbalanced)
Outputs:	8 x XLR 3 pin male (Balanced)
Mains Input:	Filtered IEC, switchable 110-120V, or 220-240V, fused, 6W max
Fuse Rating:	Anti-surge fuse 100mA 20 x 5mm (230VAC) Anti-surge fuse 250mA 20 x 5mm (115VAC)

Equipment Type

RB-UL4:	Quad stereo unbalanced to balanced converter
---------	--

Physical Specification

Dimensions (Raw):	48cm (W) x 10.8cm (D) x 4.2cm (H) (1U) 19" (W) x 4.3" (D) x 1.7" (H) (1U)
Dimensions (Boxed):	58.5cm (W) x 22.5cm (D) x 7cm (H) 23" (W) x 8.9" (D) x 2.8" (H)
Weight:	Nett: 1.3kg Gross: 1.9kg Nett: 2.9lbs Gross: 4.2lbs



The RB-UL4 is a 1U rack-mount quad stereo unit for interfacing domestic or semi-professional unbalanced equipment to professional balanced line levels.

All connections are on the rear panel. The eight RCA unbalanced inputs have

an impedance of 10kΩ and are routed to eight balanced XLR-3 outputs with an output impedance of <50Ω.

The output gain can be individually adjusted for left and right channels by using pre-set potentiometers accessible through the rear panel.

RB-LU4 Quad Stereo Balanced To Unbalanced Converter

The RB-LU4 is a 1U rack-mount quad stereo unit for interfacing professional balanced line levels to domestic or semi-pro unbalanced equipment, e.g. for connecting a pro satellite receiver to a consumer hi-fi system.

All connections are on the rear panel. The eight balanced XLR-3 inputs have an impedance of 20kΩ and are routed to eight unbalanced RCA outputs with an output impedance of <50Ω.

The output gain can be individually adjusted for left and right channels by using pre-set potentiometers accessible through the rear panel.

A LED power indicator on the front panel displays the power supply connection.



Audio Specification For RB-LU4

Maximum Input Level:	+28dBu
Input Impedance (XLR):	>20kΩ balanced bridging
Output Impedance (RCA):	<50Ω
Maximum Output Level:	+22dBu
Distortion:	0.01% THD @ 1kHz, ref +8dBu output
Noise:	-100dB, unity gain, ref +8dBu output
Common Mode Rejection:	>66dB typically
Frequency Response:	20Hz to 20kHz ±0.1dB (600Ω load, ref 1kHz)
Gain Range:	Unbalanced Output: -28dBu to 0dBu, ref 0dBu into balanced XLR input

Connections

Inputs:	8 x XLR 3 pin female (Balanced)
Outputs:	8 x RCA phono (Unbalanced)
Mains Input:	Filtered IEC, switchable 110-120V, or 220-240V, fused, 6W max
Fuse Rating:	Anti-surge fuse 100mA 20 x 5mm (230VAC) Anti-surge fuse 250mA 20 x 5mm (115VAC)

Equipment Type

RB-LU4:	Quad stereo balanced to unbalanced converter
---------	--

Physical Specification

Dimensions (Raw):	48cm (W) x 10.8cm (D) x 4.2cm (H) (1U) 19" (W) x 4.3" (D) x 1.7" (H) (1U)
Dimensions (Boxed):	58.5cm (W) x 22.5cm (D) x 7cm (H) 23" (W) x 8.9" (D) x 2.8" (H)
Weight:	Nett: 1.3kg Gross: 1.9kg Nett: 2.9lbs Gross: 4.2lbs



SONIFEX

www.sonifex.co.uk

t:+44 (0)1933 650 700

f:+44 (0)1933 650 726

sales@sonifex.co.uk

61 Station Road
Irthlingborough
Northants NN9 5QE
United Kingdom

