


PLA DL210NET

Digi-Loop™ DSP Induction Loop Amplifier



Digi-Loop is definitely state-of-the-art – the first of its kind to maximize modern amplifier technology. Its network-control capability provides seamless, remote system set-up, operation and monitoring via laptop or tablet. DSP audio processing offers flexible, powerful software control of mixing, equalization, phase compression, loop phase shift and more. Powerful Class D, pulse-width amplifiers maximize efficiency. The Digi-Loop's dual-amplifier

design offers flexibility, with the option of single 12A loop output for a perimeter loop, or dual 10A loop outputs for two loops or a loop array, or one loop/one loudspeaker. Priority input (70-100V) is also available for connection to a paging system (or distributed speaker system), ensuring announcements are heard by loop users. Use Digi-Loop with Williams Sound Digi-Wave products for crystal-clear wireless audio input.

FEATURES / BENEFITS

- DSP Audio Processing
- Digital Inputs
- LCD Screen with Metering
- Ethernet, RS-232, and USB control
- Mixing, Equalization, Compression, Phase, and Frequency-Shaping
- Power-save mode
- Master Gain Control
- High output current: 12/10 amps
- Active protection against short circuits
- XLR input configurable as microphone input or line-input, balanced or unbalanced.
- Standard 2RU, 19" rack enclosure
- Magnetic signal couples directly to devices equipped with telecoils (T-coils) such as hearing aids or cochlear implants
- Can be used with optional loop receivers
- Suitable for perimeter and low overspill phased array configuration
- Meets ADA / ADAAG guidelines

PLA DL210NET

Dimensions	2U Rackmount, 19" W x 3.5" H x 12" D. Chassis is 17" W.
Weight	14.3 lbs (6.5 kg)
Color	Case: Black, white and blue legends on front, white legends on back. LCD: Backlit Blue.
Fan Cooling	Variable Speed, Temperature Controlled
Power	100-240 VAC, 50/60 Hz, 500 Watt
Digital Input	(1x XLR); AES or EBU; 44.1kHz/48kHz
Analog Line Inputs	(1x RCA, L+R); -10dBV, 10k Ω input impedance
Mic/Line Inputs	(2x Phoenix Terminal Block); balanced or unbalanced. Input impedance: 1.5k Ω Mic, 10k Ω Line. Configurable/accepts Mic, Line +4dBu, Line +8dBu, or Line -10dBV.
70-100v Input	(1x Phoenix Terminal Block); speaker-level input, for distributed audio systems.
Line Outputs	(2x Phoenix Terminal Block); loop-through of Mic/Line inputs 1 & 2. +4dBu. Balanced or Unbalanced.
Loop Outputs	(2x Phoenix Terminal Block).
Required Loop Resistance	0.5 Ω to 1.5 Ω (DC)
Output Current (Loop)	One Loop, Output A or B: 12A rms. Two Loops, Outputs A and B: 10A rms each
Output Power (Speaker)	50 Watts X 1 Channel @ 4 Ω (35 Watts @ 8 Ω). Class D.
Loop Frequency Response	100Hz to 10kHz @400mA (Output A or B)
Speaker Frequency Response	20Hz - 20kHz (Output A)
Speaker Dynamic Range	>90 dB; A-weighted, typical
Speaker THD+N	0.07%; 50 watts into 4 Ω @ 20-20kHz
Loop THD	<1% at nominal power output, 1kHz sine wave
Front Controls	Front LCD display menu access/adjustment via control dial.
Remote Control/Configuration	Ethernet, USB, RS-232. Application "PC Mixer App" supports all 3 protocols.
Ethernet	Standard RJ-45 jack.
RS-232	Standard DB-9 COM port connector.
USB	Standard-B jack. USB 1.1, 2.0 or 3.0 supported.
Warranty	2 year limited
Approvals	CE, IC, UL, ULC, FCC, Industry Canada, RoHS, WEEE, CE, UL, CB scheme

NOTE: SPECIFICATIONS SUBJECT TO CHANGE WITHOUT NOTICE.

Digi-Loop DSP Induction Loop Amplifier

Rear View



Architectural / Engineering Specifications

The loop amplifier shall be designed for rooms of up to 6500 sq. ft. (600 sq. m) with loop signals and is the ideal solution for events and meeting venues.

It shall have one XLR digital audio input for use with digital audio sources such as pro audio MP3 players, computers with digital output, etc.

It shall have an ethernet jack to provide configuration capability over an ethernet (10 base T) network.

It shall have an RS-232 jack to provide control capability from 3rd-party controllers such as Crestron, AMX, Extron, etc.

It shall have a USB jack to provide access to internal configuration with a computer.

It shall have two MIC/LINE LEVEL inputs that can be configured as LINE (balanced) or as MICROPHONE input(s). These inputs shall be mixed with the RCA LINE inputs into one mono output for the loop.

It shall have two RCA LINE inputs that can be used to supply one or two channels of audio. These two channels shall be mixed together, then mixed with the two MIC/LINE inputs into one mono output for the loop.

It shall have a 70-100V input to provide a speaker-level input connection for use with distributed speaker systems.

It shall have two LINE OUTPUTS to provide loop-through connections for line level signals going to other equipment such as recording devices. These line outputs shall be the summed combination of the MIC/LINE LEVEL inputs and the RCA LINE inputs.

It shall have two LOOP OUTPUTS for running either one large loop, two individual loops, a phased-array system, or 1 loop + 1 speaker. Output A will be configurable in the menu to be a speaker output.

It shall provide an output of up to 12A rms on output A, for one loop with optimum loop field strength. When both outputs A and B are used, each output will supply up to 10A rms.

It shall be compatible with either US or international power systems with the appropriate power cord.

The loop amplifier shall be the Williams Sound model PLA DL210NET.

Domestic Sales

Williams Sound, LLC
10300 Valley View Rd
Eden Prairie, MN 55344
Ph: 800-328-6190 / 952-943-2252
FAX: 952-943-2174
Email: info@williamssound.com
Web: www.williamssound.com

International Sales

International Sales Department
Williams Sound, LLC
10300 Valley View Rd
Eden Prairie, MN 55344 USA
Phone: +1 952 943 2252
Fax: +1 952 943 2174
Email: info@williamssound.com
Web: www.williamssound.com



WILLIAMS SOUND®
HELPING PEOPLE HEAR

800.843.3544 / info@williamssound.com / www.williamssound.com