



## GENERAL INFORMATION

A powerful fixture in a compact body, the elektraLite **eyeBall-A** is ready to solve your solutions both big and small.

At the heart of the elektraLite **eyeBall-A** are seven 12-watt 5-in-1 LED's, consisting of a red, green, blue, amber, and white component. The 5-in-1 LED uses diffraction lensing, eliminating "rainbow" color spots which are typical when individual LED's are exposed in lighting a cyc or similar background. By mixing color internally, the **eyeBall-A**'s sophisticated diffraction lensing system provide true, blended, single-color output. Because of this, the white is perfectly blended and balanced, so as not to emit a blue-white so often seen in LED fixtures.

More than a stage and key/highlight fixture, the elektraLite **eyeBall-A** can also be used as a truss warmer or a shin kicker just as easily and effectively. With a convenient and compact strong double-yoke, mounting options are limitless.

A user-friendly onboard control interface allows for multiple control options in addition to DMX, including RGB, strobe, and console-free master/slave operation. Plug-and-play functionality is built right in!

The **eyeBall-A** has both power in and thru for easy "daisy chaining", and includes an interconnect jumper cable. The DMX connectors (both in and thru) are 5-pin XLR, however 3>5 pin and 5>3 pin turnarounds are provided for maximum flexibility.

## FEATURES

- 5-in-1 LED technology; utilizing seven 12-watt 5-way LED's
- compact design fits perfectly in 12" box truss
- flicker-free on camera operation
- strong double yoke allows for floor mount or hanging, with low-profile adjustment handles for a slim, tight contour
- variable adjustable speed strobe effect, from 0.3 to 25 FPS
- variable, adjustable fans can be set to run automatically, manually, turned off, or controlled via DMX
- RGBW 5-in-1 LED's, including 5600K white, for crisp, bright, balanced white light
- compact, lightweight design ideal for a variety of locations, including small spaces and portable applications
- up to eight fixtures can be connected on one 20A circuit, and can be run in stand-alone or master/slave configuration, all with or without a control source, for fast, effective, and efficient operation

## ORDERING INFORMATION

ELE729-10	eyeBall Quad LED with 10° Beam Spread
ELE729-25	eyeBall Quad LED with 25° Beam Spread
ELE729-40	eyeBall Quad LED with 40° Beam Spread

ELE735	eyeBall Four-Leaf Barn Door <i>(black)</i>
-W	White Finish <i>(add to end of fixture part number)</i>



# ELE729-(10, 20, or 40)

# eyeBall-A

(7) 12W RGBAW 5-in-1 LED

## SPECIFICATIONS

Power Consumption	- 85 watts (0.9A)
Electrical	- multi-voltage; AC 100-240V – 50/60Hz - IEC power (in and thru) connectors
Housing	- high temperature black polycarbonate
Materials	- corrosion resistant hardware
Yoke	- rigid flat steel
Light Engine	- seven 12-watt 5-in-1 LED emitters
Refresh Rate	- >400Hz
CRI	- 86
Optics / Lensing(s)	- Diffraction Lensing
Control	- DMX-512A (in and thru) via 5-pin XLR - 3>5 & 5>3 pin turnarounds included
Ratings / Certifications	- ETL listing to UL1573

## ACCESSORIES

Accessories Included with each eyeBall-A are as follows:

- (1) double-yoke
- (1) 24" IEC power cable with Edison connector
- (1) 108" IEC extension cable
- (1) 108" 5-pin DMX extension cable
- (1) 3>5 pin DMX turnaround
- (1) 5>3 pin DMX turnaround

## PHOTOMETRICS

Photometric data was taken with all channels at full, and reflects the output of the fixture with the lens installed as noted. Comparisons between fixtures should only be made with photometric data that incorporates the lensing system to be used.

Lens	Beam Angle	Field Angle	Candela (cd)	Field Lumens	Lumens per Watt
10°	11°	19°	74,221	1498	21.4
25°	22°	36°	74,103	1383	19.7
40°	39°	53°	73,639	1369	19.5

Lens	Beam Size at 10' Throw (d)	Beam Size at 20' Throw (d)	Beam Size at 30' Throw (d)
10°	6'-3"	11'-9"	19'-2"
25°	8'-4"	15'-3"	23'-4"
40°	10'-9"	21'-10"	28'-1"

To determine illumination in footcandles (fc) at any distance, divide candlepower (cd) by distance squared ( $fc=cd/(d^2)$ ).  
For Lux, multiply footcandles (fc) by 10.76.

## DMX PROFILE

Depending on personality chosen, the eyeBall-A can be set for operation from 4 to 11 channels of DMX. Consult the User Manual for further details.

CH	ACTION DESCRIPTION	VALUE
1	Grand Master for RGBW	0-255
2	RED LED's	0-255
3	GREEN LED's	0-255
4	BLUE LED's	0-255
5	WHITE LED's	0-255
6	Linear Dimmer Speed (DIM=OFF)	0-50
	Nonlinear Speed 1 (DIM1)	51-100
	Nonlinear Speed 2 (DIM2)	101-150
	Nonlinear Speed 3 (DIM3)	151-200
	Nonlinear Speed 4 (DIM4)	201-255

\* = consult manual for full DMX Profile details

## DIMENSIONS CHART

Physical Dimensions			Shipping Dimensions		
Length	Width	Height	Length	Width	Height
8.6"	6.5"	6.5"	15"	9"	9"

## WEIGHTS CHART

Weight		Shipping Weight	
lbs	kgs	lbs	kgs
4.6	2.0	8.0	3.6

