



100V 115/120V 230/240V

Eos® Series



GENERAL INFORMATION

The ETCnomad Puck lighting controller is a full-featured mini-computer with an embedded ETCnomad lighting control key capable of running Eos and Element™ applications. It provides lighting control with conventional and moving lights, media servers and LED luminaires. The ETCnomad Puck lighting controller can be used in primary, backup, client and offline environments.

Optional fader wings, programming wings, X-keys and compatibility with USB–MIDI panels allow extended and customizable control.

FEATURES

- The base unit is 512 outputs. This can be upgraded to 6,144 outputs
- The ETCnomad Puck 512 lighting controller makes an ideal tech table RVI
- Operates in stand-alone, primary, backup and client environments
- When connected as a client, output capacity is determined by the system to which it is connected
- Net3™/ACN/sACN and ArtNet Ethernet lighting protocols
- DMX/RDM via ETC Gadget™ or Gadget™ 2
- DMX/RDM via Net3 DMX/RDM Gateways
- One HDMI and one Mini Display Port (Mini Display Port to HDMI converter included)
- Four USB ports
- OSC Transmit/Receive
- UDP Transmit/Receive

See Eos and Element datasheets and operation manuals for ETCnomad lighting control features

ACCESSORIES

- Eos Programming Wing
- Eos Motorized Fader Wings (10 or 20)
- Eos Standard Fader Wings (20 or 40)
- ETCpad
- aRFR/iRFR remote controls
- Alphanumeric keyboard
- USB mouse

ORDERING INFORMATION

ETCnomad Puck Lighting Controller

MODEL	DESCRIPTION
ETCnomad Puck512	ETCnomad Puck 512 Lighting Controller Kit, 512 outputs and RVI
ETCnomad Puck6144	ETCnomad Puck 6,144 Lighting Controller Kit, 6,144 outputs
ETCnomad 5.5K Up	After-sale output upgrade to 6144

IMPORTANT ETCNOMAD LIGHTING CONTROLLER ORDERING INFORMATION

Local DMX output may be distributed using an Gadget 2 USB to DMX/RDM converter. Up to four DMX outputs are supported. Additional or all outputs may be distributed via Ethernet protocols directly (Net3™/ACN/sACN, or ArtNet) or by compatible Ethernet-distribution hardware, such as Net3 DMX/RDM Gateways. The Gadget and network equipment must be purchased separately from the ETCnomad Puck lighting control kit.

Note: The ETCnomad Puck lighting controller does not support ETCNet2™/EDMX protocol.

Note: ETCnomad Puck is also compatible with Cobalt.

Important Note: The original Puck (with three USB ports) can be upgraded to 2,048 outputs only. Use ETCnomad 1.5K Up to order an after-sale upgrade for this unit.

Ships with:

- US power cord
- Mini Display Port to HDMI adapter
- VESA mounting bracket



