Specifications



DISTRO9 HDR™

Antenna Distribution System





2 Input Zones, each with 2x (Diversity) RF inputs provide maximum flexibility for covering large areas or multiple rooms, with DC power available for in-line amplifiers or active antennas.

Any of the DISTRO9's clean unity gain RF outputs can be cascaded to a second DISTRO9, eliminating the need for dedicated cascade ports and providing up to 17 wireless microphone channels in just 2RU of rack space.

With superior gain flatness across VHF, T-Band, and UHF, the DISTRO9 HDR is built for the rapidly changing RF spectrum landscape worldwide.

NOTE: DC bias from receivers MUST be switched OFF before connecting receivers to outputs. Failure to turn DC bias OFF may result in damage to the device. The DC Power-to-Antenna output is factory-set to the 'Off' position. To turn the Power-to-Antenna function 'On', the switch must be moved to the 'On' position. However, access to this switch requires opening the DISTRO9 housing cover, which can involve the risk of electric shock; see WARNING below.

SKU **DISTRO9HDR** Includes:

(1) DISTRO9 HDR Antenna Distribution System (1) AC power cord

WARNING

- DC bias MUST be switched OFF before connecting receivers to outputs.
 Failure to turn DC bias OFF may result in damage to the device.
- Do not expose this appliance to heat or moisture
- To avoid shock, do not remove cover
- Always plug the unit into a grounded receptacle
- Refer all service to qualified service personnel or distributors.

Specifications

Frequency range	50-1000 MHz (VHF, UHF, +900 bands)
RF output level (gain)	± 3dB
	60dB @ 510MHz, 80dB @ 200 MHz
Third order intercept point	15dBm @ VHF, 20+ @ UHF
Impedance	50Ω
	50/60 HZ, 2A
Fuse	
	100-240 VAC
DC over coax (to external ante	ennas) 12 VDC 100mA
Output DC voltage (to receive	r jacks)12V 3A
Output DC connectors	Anderson Power Pole
Dimensions	
	2(H) X 10(D) in
Unit Weight	2.7 Ka / 6lbs