

# Remote Power Packs

---

DCA100-1

The DCA100-1 DC to DC converter allows use of a mixer with mobile, belt pack and gel cell 6 to 18 VDC battery power. The DCA100-1 can mount directly to the underside of the mixer with the screws provided or fit into the slide mounts of the PROK-1 for easy interchange with battery packs.

The DCA100-1 DC to DC Converter accepts inputs from 6 to 18 VDC and outputs 24VDC to operate a mixer from 6.0 or 7.2V camcorder Ni-Cd, belt-pack Ni-Cd packs, automotive 12V or 12.0 to 14.4 V NP-1 batteries. The DCA100-1 requires a standard 4 pin XLR input connector from the battery source (pin 4 positive, pin 1 ground). Battery clips (Hawk-Woods Co. # NPA - XLR) are available for NP-1 type 13.2V NiMH batteries, which can power a MXS100 thru a DCA100 for up to 10 hours.

Image  
Coming  
Soon

# Remote Power Packs

## Technical Specifications

DCA100-1

<b>POWER</b>	DC to DC converter powers units from 12VDC mobile.
<b>POWER SUPPLY</b>	Supplies 24VDC @ .2amp maximum.
<b>COMPATABILITY</b>	Functional with: MX100 MX100C MX101 XP100 MX200 MX200C MXS100 XPS100 XPS200
<b>INPUTS</b>	6 to 18 VDC
<b>OUTPUTS</b>	24VDC
<b>INPUT CONNECTOR</b>	A standard 4 pin XLR input connector from the battery source (pin 4 positive, pin 1 ground).
<b>WARRANTY</b>	Limited, One Year Warranty