PLC-XU300

XGA Ultraportable Multimedia Projector



COMPLETE EASY AUTO SET UP FUNCTION, SMART AUTO INPUT SEARCH AND AUTO VERTICAL KEYSTONE CORRECTION

PLC-XU300 provides "Auto Set Up Function" that corrects keystone shaped distortion by searching for an input signal and detecting projector incline, therefore reducing set up time. PLC-XU300 automatically compensates for keystone picture distortion. Auto Keystone Correction, Auto Input Search and Auto PC Adjustment make it a really smart projector.

NETWORKING CAPABILITY

Bright 3000Im, the PLC-XU300 is equipped with SANYO's exclusive PJ-Net Master Network Interface software for wired and wireless networking, a common feature among SANYO's extensive line of commercial projectors. Networking allows the monitoring of projector functions and operation from a long distance via a web browser for up 15,000 Sanyo projectors. Emails can be sent automatically to report operating status.

SHORT THROW LENS WITH 1.2 ZOOM AND 1W SPEAKER

PLC-XU300 is equipped with a zoom lens that allows screen size adjustment. The optical zoom works to maintain the image quality. The short-focus type lens allows large screen image projections with a short throw distance. The PLC-XU300 enables 100-inch screen projection at the shortest distance, 83 inches. Along with its mobility, the PLC-XU300 features a high-output 1 Watt speaker. Sufficient audio is delivered through its built-in speaker, so the projector can be used in small conference rooms, classrooms, and other similar spaces.

BLACK BOARD / COLOR BOARD MODE

What could be more right for education? A black board mode. The PLC-XU300 is compatible with four colored (red, blue, green and yellow) projection surfaces via the 'Color Board Mode'. It adjusts the color to make images look as true as on an ordinary white screen.

LAMP REPLACEMENT ON TOP CABINET

There is access to the lamp from the top of the projector which means you can replace the lamp on a ceiling-mounted unit without taking down the projector.

CLOSED CAPTION

PLC-XU300 Closed Caption compatible.





PRESENTATION TECHNOLOGIES

21605 Plummer Street Chatsworth, CA 91311 Ph: 888-337-1215 (toll-free) Fax 818.717.2719 www.sanyoprojectors.com Specifications

Resolution XGA (1,024 x 768)		ре	cifications
Uniformity	Resolution		XGA (1,024 x 768)
Panel System			
Number of Pixels			
Contrast Ratio (Full on / off) 500.1 Image Size			
Image Size			
Aspect Ratio			
Projection Lamp (s)	Image Size		
Scanning Frequency			11.
Dot Clock 140MHz Fan Noise 29dBA(EO) 34dBA(Normal) Voltage 100-240V BTU Rating 1,126 (Normal) 860W(Eco) Power Consumption 330W (Normal) 252W(Eco) Input signal compatibility UXGA / WXCA / SXGA + / SXGA / SVGA / VGA / VGA / WACA, 480If 480p / 575i / 575p / 720p / 1080i Color System NTSC / PAL / SECAM / NTSC4.43 / PAL-M/ PAL-N Projection Lens (inch) F1.65 – 1.76 f = 0.88° - 1.06° Throw Ratio 1.74 - 2.09 Throw Distance (feet) 4.6° - 41.7° Zoom / Focus Manual Zoom Alio 9:1 Up / Down Ratio 9:1 Digital Keystone Correction V + 9:3° (Auto Keystone) Projection System Diachronic mirror & X prism system w/PBS Digital Keystone Correction V + 9:3° (Auto Keystone) Projection System Diachronic mirror & X prism system w/PBS Digital Keystone Correction V + 30° (Auto Keystone) Projection System Diachronic mirror & X prism system w/PBS Digital Keystone Correction V + 30° (Auto Keystone) Projection System Diachronic mirror & X prism system w/PBS	Projection Lamp (s)		
Fan Noise			
Voltage			
BTU Rating			
Dower Consumption			
Input signal compatibility			
MAC, 480i / 480p / 575i / 575p / 720p / 1080i Color System	Power Consumption		
MAC., 480 / 1480 / 1575 / 1575 / 1570 / 1080	. , ,		
Projection Lens (inch)			
Throw Ratio			
Throw Distance (feet)			
Zoom / Focus			
Time			
Digital Keystone Correction			
Digital Keystone Correction Projection System Diachronic mirror & X prism system w/PBS Digital Zoom Speaker Output Weight (lbs.) Dimensions (inch) W,H,D Replacement Lamp Replacement Remote PC1 Input Input PC2 Input Out Put Control 1 Others Discording A x 1 (Memory viewer) Included Accessories Optional Accessories Optional Accessories Diachronic mirror & X prism system w/PBS Diachronic mirror & X prism system w/PBS Indiach x 1 (Audio injur) 100			
Projection System Diachronic mirror & X prism system w/PBS Digital Zoom 16x - 1/4x Speaker Output TW Weight (lbs.) Dimensions (inch) W,H,D Replacement Lamp Replacement Remote PC1 Dsub-15 x 1 (RGB, Component, Scart RGB) Mini jack x 1 (Audio input, stereo) Dsub-15 x 1 (in common) Mini jack x 1 (Composite Video) RCA x 2 (Audio input, R/ L-mono) Dsub-15 x 1 (in common) Mini jack x 1 (Audio out, stereo variable) Control 1 Others Dsub-9 x 1 (Control port) USB-B x 1 (Mouse control) RJ-45 x 1 (Memory viewer) Quick reference guide, CD-ROM read me note, UL cable card, PIN code label, Computer cable, Power cord, Remote control, AAA Battery x 2, User's manual (CD ROM), Network PJ-Net Manager software (CD ROM), Soft carrying case, Strap for Lens cap Optional Accessories Diachronic mirror & X prism system w/PBS 1W 1W 1W 1W 1W 1W 1W 1W 1W 1DB-15 x 1 (in common) Mini jack x 1 (Audio input, stereo) 1Dsub-15 x 1 (in common) Mini jack x 1 (Audio out, stereo variable) Dsub-9 x 1 (Control port) USB-B x 1 (Mouse control) RJ-45 x 1 (Wired LAN) USB-A x 1 (Memory viewer) Quick reference guide, CD-ROM read me note, UL cable card, PIN code label, Computer cable, Power cord, Remote control, AAA Battery x 2, User's manual (CD ROM), Network PJ-Net Manager software (CD ROM), Soft carrying case, Strap for Lens cap Optional Accessories POA-CACOMPVGA-Component Video Cable User Maintenance Clean air filters, replace lamp assembly Three years parts and labor; 90 days original lamp;			
Digital Zoom			
Speaker Output 1W Weight (lbs.) 5.7lbs.			
Dimensions (inch) W,H,D 12.8"x3.3x9.1			16x - 1/4x
Dimensions (inch) W,H,D 12.8"x3.3x9.1 Replacement Lamp 610 343 2069 Replacement Remote 645 099 3213 Input PC1 Dsub-15 x 1 (RGB, Component, Scart RGB) Mini jack x 1 (Audio input, stereo) Dsub-15 x 1 (in common) Mini jack x 1 (Audio input, stereo) Mini DIN 4-pin x 1 (S-Video) RCA x 2 (Audio input, R/ L-mono) RCA x 2 (Audio input, R/ L-mono) Dsub-15 x 1 (in common) Mini jack x 1 (Audio out, stereo variable) Control 1 Dsub-9 x 1 (Control port) USB-B x 1 (Mouse control) RJ-45 x 1 (Wired LAN) USB-A x 1 (Memory viewer) Quick reference guide, CD-ROM read me note, UL cable card, PIN code label, Computer cable, Power cord, Remote control, AAA Battery x 2, User's manual (CD ROM), Network PJ-Net Manager software (CD ROM), Soft carrying case, Strap for Lens cap Optional Accessories POA-CACOMPVGA-Component Video Cable User Maintenance Clean air filters, replace lamp assembly Three years parts and labor; 90 days original lamp;			
Replacement Lamp Replacement Remote			
Replacement Remote 645 099 3213 PC1 Dsub-15 x 1 (RGB, Component, Scart RGB) Mini jack x 1 (Audio input, stereo) Dsub-15 x 1 (in common) Mini jack x 1 (Audio input, stereo) Mini DIN 4-pin x 1 (S-Video) RCA x 1 (Composite Video) RCA x 2 (Audio input, R/ L-mono) Dsub-15 x 1 (in common) Mini jack x 1 (Audio out, stereo variable) Dsub-9 x 1 (Control port) USB-B x 1 (Mouse control) RJ-45 x 1 (Wired LAN) USB-A x 1 (Memory viewer) Ouick reference guide, CD-ROM read me note, UL cable card, PIN code label, Computer cable, Power cord, Remote control, AAA Battery x 2, User's manual (CD ROM), Network PJ-Net Manager software (CD ROM), Soft carrying case, Strap for Lens cap Optional Accessories POA-CACOMPVGA-Component Video Cable User Maintenance Clean air filters, replace lamp assembly Three years parts and labor; 90 days original lamp;			
Input PC1 Dsub-15 x 1 (RGB, Component, Scart RGB) Mini jack x 1 (Audio input, stereo) Dsub-15 x 1 (in common) Mini jack x 1 (Audio input, stereo) Mini DIN 4-pin x 1 (S-Video) RCA x 1 (Composite Video) RCA x 2 (Audio input, R/ L-mono) Dsub-15 x 1 (in common) Mini jack x 1 (Audio out, R/ L-mono) Dsub-15 x 1 (in common) Mini jack x 1 (Audio out, stereo variable) Dsub-9 x 1 (Control port) USB-B x 1 (Mouse control) RJ-45 x 1 (Wired LAN) USB-A x 1 (Wemory viewer) Ouick reference guide, CD-ROM read me note, UL cable card, PIN code label, Computer cable, Power cord, Remote control, AAA Battery x 2, User's manual (CD ROM), Network PJ-Net Manager software (CD ROM), Soft carrying case, Strap for Lens cap Optional Accessories POA-CACOMPVGA-Component Video Cable User Maintenance Clean air filters, replace lamp assembly Three years parts and labor; 90 days original lamp;			
Input PC1	Replacement Remote		
Input PC2 Dsub-15 x 1 (in common)		DC1	
Input Mini jack x 1 (Audio input, stereo)			
Input Mini Jack x 1 (Audio input, stereo)	Input		
Out Put Out Put Dsub-15 x 1 (in common) Mini jack x 1 (Audio out, stereo variable) Control 1 Others RCA x 2 (Audio input, R/ L-mono) Dsub-15 x 1 (in common) Mini jack x 1 (Audio out, stereo variable) Dsub-9 x 1 (Control port) USB-B x 1 (Mouse control) RJ-45 x 1 (Wired LAN) USB-A x 1 (Memory viewer) Ouick reference guide, CD-ROM read me note, UL cable card, PIN code label, Computer cable, Power cord, Remote control, AAA Battery x 2, User's manual (CD ROM), Network PJ-Net Manager software (CD ROM), Soft carrying case, Strap for Lens cap Optional Accessories POA-CACOMPVGA-Component Video Cable User Maintenance Clean air filters, replace lamp assembly Three years parts and labor; 90 days original lamp;			
Out Put Day		VIDEO	
Out Put Dsub-15 x 1 (in common)			RCA x 1 (Composite Video)
Mini jack x 1 (Audio out, stereo variable) Control 1 Dsub-9 x 1 (Control port) USB-B x 1 (Mouse control) RJ-45 x 1 (Wired LAN) USB-A x 1 (Memory viewer) Ouick reference guide, CD-ROM read me note, UL cable card, PIN code label, Computer cable, Power cord, Remote control, AAA Battery x 2, User's manual (CD ROM), Network PJ-Net Manager software (CD ROM), Soft carrying case, Strap for Lens cap Optional Accessories POA-CACOMPVGA-Component Video Cable User Maintenance Clean air filters, replace lamp assembly Three years parts and labor; 90 days original lamp;			
Control 1 Dsub-9 x 1 (Control port) USB-B x 1 (Mouse control) RJ-45 x 1 (Wired LAN) USB-A x 1 (Memory viewer) Ouick reference guide, CD-ROM read me note, UL cable card, PIN code label, Computer cable, Power cord, Remote control, AAA Battery x 2, User's manual (CD ROM), Network PJ-Net Manager software (CD ROM), Soft carrying case, Strap for Lens cap Optional Accessories POA-CACOMPVGA-Component Video Cable User Maintenance Clean air filters, replace lamp assembly Three years parts and labor; 90 days original lamp;	Out Put		
Others USB-B x 1 (Mouse control) RJ-45 x 1 (Wired LAN) USB-A x 1 (Wemory viewer) Ouick reference guide, CD-ROM read me note, UL cable card, PIN code label, Computer cable, Power cord, Remote control, AAA Battery x 2, User's manual (CD ROM), Network PJ-Net Manager software (CD ROM), Soft carrying case, Strap for Lens cap Optional Accessories POA-CACOMPVGA-Component Video Cable User Maintenance Clean air filters, replace lamp assembly Three years parts and labor; 90 days original lamp;			
Others RJ-45 x 1 (Wouse control) RJ-45 x 1 (Wired LAN) USB-A x 1 (Wemory viewer) Quick reference guide, CD-ROM read me note, UL cable card, PIN code label, Computer cable, Power cord, Remote control, AAA Battery x 2, User's manual (CD ROM), Network PJ-Net Manager software (CD ROM), Soft carrying case, Strap for Lens cap Optional Accessories POA-CACOMPVGA-Component Video Cable User Maintenance Clean air filters, replace lamp assembly Three years parts and labor; 90 days original lamp;	Control 1		
Others RJ-45 x 1 (Wired LAN) USB-A x 1 (Memory viewer) Quick reference guide, CD-ROM read me note, UL cable card, PIN code label, Computer cable, Power cord, Remote control, AAA Battery x 2, User's manual (CD ROM), Network PJ-Net Manager software (CD ROM), Soft carrying case, Strap for Lens cap Optional Accessories POA-CACOMPVGA-Component Video Cable User Maintenance Clean air filters, replace lamp assembly Three years parts and labor; 90 days original lamp;			USB-B x 1 (Mouse control)
USB-A x 1 (Memory viewer) Quick reference guide, CD-ROM read me note, UL cable card, PIN code label, Computer cable, Power cord, Remote control, AAA Battery x 2, User's manual (CD ROM), Network PJ-Net Manager software (CD ROM), Soft carrying case, Strap for Lens cap Optional Accessories POA-CACOMPVGA-Component Video Cable User Maintenance Clean air filters, replace lamp assembly Three years parts and labor; 90 days original lamp;	Others		
Ouick reference guide, CD-ROM read me note, UL cable card, PIN code label, Computer cable, Power cord, Remote control, AAA Battery x 2, User's manual (CD ROM), Network PJ-Net Manager software (CD ROM), Soft carrying case, Strap for Lens cap Optional Accessories POA-CACOMPVGA-Component Video Cable User Maintenance Clean air filters, replace lamp assembly Three years parts and labor; 90 days original lamp;			
card, PIN code label, Computer cable, Power cord, Remote control, AAA Battery x 2, User's manual (CD ROM), Network PJ-Net Manager software (CD ROM), Soft carrying case, Strap for Lens cap Optional Accessories POA-CACOMPVGA-Component Video Cable User Maintenance Clean air filters, replace lamp assembly Three years parts and labor; 90 days original lamp;	Included Accessories		•
Included Accessories control, AAA Battery x 2, User's manual (CD ROM), Network PJ-Net Manager software (CD ROM), Soft carrying case, Strap for Lens cap Optional Accessories POA-CACOMPVGA-Component Video Cable User Maintenance Clean air filters, replace lamp assembly Three years parts and labor; 90 days original lamp;			
PJ-Net Manager software (CD ROM), Soft carrying case, Strap for Lens cap Optional Accessories POA-CACOMPVGA-Component Video Cable User Maintenance Clean air filters, replace lamp assembly Three years parts and labor; 90 days original lamp;			
Strap for Lens cap Optional Accessories POA-CACOMPVGA-Component Video Cable User Maintenance Clean air filters, replace lamp assembly Three years parts and labor; 90 days original lamp;			
Optional Accessories POA-CACOMPVGA-Component Video Cable User Maintenance Clean air filters, replace lamp assembly Three years parts and labor; 90 days original lamp;			
User Maintenance Clean air filters, replace lamp assembly Three years parts and labor; 90 days original lamp;	Ontional Accessories		
Warranty Three years parts and labor; 90 days original lamp;	·		
	User Maintenance		
Quick Repair Program under warranty	Warranty	_	
	vvarranty		Quick Repair Program under warranty

Because its products are subject to continuous improvement, SANYO reserves the right to modify product design and specifications without notice and without incurring any obligations.



Issued 3/09 ©2009 SANYO