PLC-XU355

XGA Ultraportable Multimedia Projector



A SIMPLE WIRELESS SETTING FOR USE WITH A USB MEMORY

The PLC-XU355 has an innovative wireless feature called "Simple Wireless Set Up" .This model can set up a wireless connection easily without installing a software from a CD-ROM. Just pass off the USB memory. By connecting the PC and USB memory, the program in the PLC-XU355 starts running automatically, and the image will be projected directly on the screen.

NETWORKING CAPABILITY

Bright 3500Im, the PLC-XU355 is equipped with SANYO's exclusive PJ-Net Master Network Interface software for wired and wireless networking, a common feature among SANYO's extensive line of commercial projectors. Networking allows the monitoring of projector functions and operation from a long distance via a web browser for up 15,000 Sanyo projectors. Emails can be sent automatically to report operating status.

COMPLETE EASY AUTO SET UP FUNCTION, SMART AUTO INPUT SEARCH AND AUTO VERTICAL KEYSTONE CORRECTION

PLC-XU355 provides "Auto Set Up Function" that corrects keystone shaped distortion by searching for an input signal and detecting projector incline, therefore reducing set up time. PLC-XU355 automatically compensates for keystone picture distortion. Auto Keystone Correction, Auto Input Search and Auto PC Adjustment make it a really smart projector.

SHORT THROW LENS WITH 1.6 ZOOM AND 7W SPEAKER

PLC-XU355 is equipped with a zoom lens that allows screen size adjustment. The optical zoom works to maintain the image quality. The short-focus type lens allows large screen image projections with a short throw distance. The PLC-XU355 enables 100-inch screen projection at the shortest distance, 80 inches. Along with its mobility, the PLC-XU355 features a high-output 7 Watt speaker. Sufficient audio is delivered through its built-in speaker, so the projector can be used in conference rooms, classrooms, and other similar spaces.

BLACK BOARD / COLOR BOARD MODE

What could be more right for education? A black board mode. The PLC-XU355 is compatible with four colored (red, blue, green and yellow) projection surfaces via the 'Color Board Mode'. It adjusts the color to make images look as true as on an ordinary white screen.

LAMP REPLACEMENT ON TOP CABINET

There is access to the lamp from the top of the projector which means you can replace the lamp on a ceiling-mounted unit without taking down the projector.





PRESENTATION TECHNOLOGIES

21605 Plummer Street Chatsworth, CA 91311 Ph: 888-337-1215 (toll-free) Fax 818.717.2719 www.sanyoprojectors.com

Specifications

		cifications
Resolution		XGA (1,024 x 768)
Brightness (typical)		3500 Alm
Uniformity		85%
Panel System		0.63" TFT Polyx3
Number of Pixels		2,359.296 (786,432 x3)
Contrast Ratio (Full on / off)		500:1
Image Size		30"-300"
Aspect Ratio		4:3
Projection Lamp (s)		225W UHP
Scanning Frequency		H:15-100kHZ, V:50-100Hz
Dot Clock		140MHz
Fan Noise		29dBA(Eco) 34dBA(Normal)
Voltage		100-240V
BTU Rating		1,126 (Normal) 860W(Eco)
Power Consumption		330W (Normal) 252W(Eco)
Input signal compatibility		UXGA / WXGA / SXGA+ / SXGA / XGA / SVGA / VGA /
		MAC, 480i / 480p / 575i / 575p / 720p / 1080i
Color System		NTSC / PAL / SECAM / NTSC4.43 / PAL-M / PAL-N
Projection Lens (inch)		F1.65 – 2.33 f=0.61" - 0.97"
Throw Ratio		1.18-1.91:1
Throw Distance (feet)		2.26' - 23.72'
Zoom / Focus		Manual
Zoom Ratio		1:1.6
Up / Down Ratio		9:1
Digital Keystone Correction		V +/- 30° (Auto Keystone)
Projection System		Diachronic mirror & X prism system w/PBS
Digital Zoom		16x - 1/4x
Speaker Output		7W
Weight (lbs.)		6.4 lbs
Dimensions (inch) W,H,D		17.3"x9.4"x16.9"
Replacement Lamp		610 343 2069
Replacement I		645 099 3220
INPUT	PC1	Dsub-15 x 1 (RGB, Component, RGB)
INFUI		Mini jack x 1 (Audio input, stereo)
	PC2	DVI-I x 1 (Digital & Analog)
		Mini jack x 1 (Audio input, stereo)
		Mini DIN 4-pin x 1 (S-Video)
	VIDEO	RCA x 1 (Composite Video)
	VIDEO	
		L RCA x 2 (Audio input R/ L-mono)
		RCA x 2 (Audio input, R/ L-mono) Dsub-15 x 1 (Monitor out)
OU	T PUT	Dsub-15 x 1 (Monitor out)
	T PUT	Dsub-15 x 1 (Monitor out) Mini jack x 1 (Audio out, Stereo variable)
		Dsub-15 x 1 (Monitor out) Mini jack x 1 (Audio out, Stereo variable) Dsub-9 x 1 (Control port)
	T PUT	Dsub-15 x 1 (Monitor out) Mini jack x 1 (Audio out, Stereo variable) Dsub-9 x 1 (Control port) USB-B x 1 (Mouse control)
	T PUT	Dsub-15 x 1 (Monitor out) Mini jack x 1 (Audio out, Stereo variable) Dsub-9 x 1 (Control port) USB-B x 1 (Mouse control) RJ-45 x 1 (Wired LAN)
CON	T PUT	Dsub-15 x 1 (Monitor out) Mini jack x 1 (Audio out, Stereo variable) Dsub-9 x 1 (Control port) USB-B x 1 (Mouse control) RJ-45 x 1 (Wired LAN) USB-A x 1 (Memory viewer)
CON	T PUT	Dsub-15 x 1 (Monitor out) Mini jack x 1 (Audio out, Stereo variable) Dsub-9 x 1 (Control port) USB-B x 1 (Mouse control) RJ-45 x 1 (Wired LAN) USB-A x 1 (Memory viewer) User's manual (CD ROM),UL cable card, Computer cable
CON	T PUT TROL 1	Dsub-15 x 1 (Monitor out) Mini jack x 1 (Audio out, Stereo variable) Dsub-9 x 1 (Control port) USB-B x 1 (Mouse control) RJ-45 x 1 (Wired LAN) USB-A x 1 (Memory viewer) User's manual (CD ROM),UL cable card, Computer cable (Dsub15—Dsub15),Power cord, Remote control, AAA
CON	T PUT TROL 1	Dsub-15 x 1 (Monitor out) Mini jack x 1 (Audio out, Stereo variable) Dsub-9 x 1 (Control port) USB-B x 1 (Mouse control) RJ-45 x 1 (Wired LAN) USB-A x 1 (Memory viewer) User's manual (CD ROM),UL cable card, Computer cable (Dsub15—Dsub15),Power cord, Remote control, AAA Battery x 2, Network Viewer & Capture software (CD
CON	T PUT TROL 1	Dsub-15 x 1 (Monitor out) Mini jack x 1 (Audio out, Stereo variable) Dsub-9 x 1 (Control port) USB-B x 1 (Mouse control) RJ-45 x 1 (Wired LAN) USB-A x 1 (Memory viewer) User's manual (CD ROM),UL cable card, Computer cable (Dsub15—Dsub15),Power cord, Remote control, AAA Battery x 2, Network Viewer & Capture software (CD ROM),Easy wireless setup software (USB Memory), Soft
OTHERS Included Acces	T PUT TROL 1 ssories	Dsub-15 x 1 (Monitor out) Mini jack x 1 (Audio out, Stereo variable) Dsub-9 x 1 (Control port) USB-B x 1 (Mouse control) RJ-45 x 1 (Wired LAN) USB-A x 1 (Memory viewer) User's manual (CD ROM),UL cable card, Computer cable (Dsub15 — Dsub15),Power cord, Remote control, AAA Battery x 2, Network Viewer & Capture software (CD ROM),Easy wireless setup software (USB Memory), Soft carrying case, Strap for Lens cap
CON	T PUT TROL 1 ssories	Dsub-15 x 1 (Monitor out) Mini jack x 1 (Audio out, Stereo variable) Dsub-9 x 1 (Control port) USB-B x 1 (Mouse control) RJ-45 x 1 (Wired LAN) USB-A x 1 (Memory viewer) User's manual (CD ROM),UL cable card, Computer cable (Dsub15—Dsub15),Power cord, Remote control, AAA Battery x 2, Network Viewer & Capture software (CD ROM),Easy wireless setup software (USB Memory), Soft carrying case, Strap for Lens cap POA-CACOMPVGA-Component Video Cable
OTHERS Included Acces	T PUT TROL 1 ssories	Dsub-15 x 1 (Monitor out) Mini jack x 1 (Audio out, Stereo variable) Dsub-9 x 1 (Control port) USB-B x 1 (Mouse control) RJ-45 x 1 (Wired LAN) USB-A x 1 (Memory viewer) User's manual (CD ROM),UL cable card, Computer cable (Dsub15—Dsub15),Power cord, Remote control, AAA Battery x 2, Network Viewer & Capture software (CD ROM),Easy wireless setup software (USB Memory), Soft carrying case, Strap for Lens cap POA-CACOMPVGA-Component Video Cable Clean air filters, replace lamp assembly
OTHERS Included Acces Optional Acces	T PUT TROL 1 ssories	Dsub-15 x 1 (Monitor out) Mini jack x 1 (Audio out, Stereo variable) Dsub-9 x 1 (Control port) USB-B x 1 (Mouse control) RJ-45 x 1 (Wired LAN) USB-A x 1 (Memory viewer) User's manual (CD ROM),UL cable card, Computer cable (Dsub15—Dsub15),Power cord, Remote control, AAA Battery x 2, Network Viewer & Capture software (CD ROM),Easy wireless setup software (USB Memory), Soft carrying case, Strap for Lens cap POA-CACOMPVGA-Component Video Cable

Because its products are subject to continuous improvement, SANYO reserves the right to modify product design and specifications without notice and without incurring any obligations.



Rear Back Panel

Issued 1/09 ©2009 SANYO