



BlueKeeper

WIRELESS AUDIO GATEWAY

CE

FEATURES

- Bluetooth Wireless Technology
- XLR input (mic / line switch)
- XLR Caller Output
- 3.5 mm stereo line input
- 3.5 mm stereo line output
- 3.5 mm mono mic level output
- Headphone jack, 3.5mm stereo, mixed send and caller.
- Send and Caller signal level LEDs

JK Audio combines Bluetooth Wireless Technology with professional audio electronics in a convenient desktop design. BlueKeeper allows you to send mic and line level signals into your wireless phone while maintaining excellent separation between your voice and the caller. The stereo output jack on the back of the unit provides your voice on one channel and only the caller's voice on the other channel. The balanced XLR output jack contains only the caller's voice.


BlueKeeper pairs to your cell phone like a Bluetooth wireless headset. This professional microphone preamplifier provides a dramatic improvement in sound quality. BlueKeeper also pairs to Bluetooth equipped sound cards and music players in full bandwidth stereo A2DP mode.

The 3.5 mm stereo line input jack allows recordings to be sent into the Bluetooth device. The 3.5 mm stereo line output jack provides your full bandwidth send mix on the left channel and Bluetooth caller audio on the right channel. The headphone output gives you a mix of the XLR input, 3.5 mm input, and Bluetooth audio. This same overall mix is also provided on a 3.5 mm mono mic level output jack. This output is perfect for connection to the mic input jack on voice recorders or notebook computers. Your voice will remain in full bandwidth high fidelity while the caller's voice, well... it sounds as good as it can over a mobile phone.

JK Audio

BlueKeeper

WIRELESS AUDIO GATEWAY



Specifications

| Input | | | Output | | | |
|------------|--|--|--|---|--|--|
| | Balanced Female XLR | 1/8" (3.5mm) Stereo | Balanced Male XLR | Unbalanced 1/8"(3.5mm) Mono | Unbalanced 1/8" (3.5mm) Stereo | Headphone 1/8" (3.5mm) Stereo |
| Impedance: | 1 k ohms | 20k ohms | 200 ohms | 50 ohms | 50 ohms | 8 ohms |
| Level: | 15 mV RMS (-34 dBu) nom Mic/Line pad switch = +6 dBu max | 250 mV RMS (-10 dBu nom) +6dBu max | 500 mV RMS (-4 dBu) nom +14 dBu max Caller Only | 15mv RMS (-34dBu nom.) Mixed Send and Caller | 250 mV RMS (-10dBu nom.) +6 dBu max Left = Send Right = Caller | ½ watt Mixed Send and Caller |

Bluetooth

| Standard: | Bluetooth 2.0 | Frequency | Headset mode (phone): 300 Hz - 3400 Hz Headphone mode: 30Hz - 17 kHz | | | |
|-----------|--------------------------|-----------|---|--|--|--|
| Distance: | 25 feet (8 meters) | Response: | | | | |
| | | | | | | |
| Power: | 120-240 VAC power supply | Ciza | 7" x 6" x 1.6" | | | |
| Weight: | 2.2 lbs. (1kg) | Size. | 7" x 6" x 1.6" (18 x 15 x 4.2 cm) | | | |

The *Bluetooth* word mark and logos are owned by the *Bluetooth* SIG, Inc. and any use of such marks by JK Audio, Inc. is under license. Other trademarks and trade names are those of their respective owners.

