RM-II5 & RM-I20 POWER MONITOR AND CONDITIONER from EMERSON NETWORK POWER



What's the current load on your circuit? What's the voltage? Is the generator operating at the right frequency?. By the way, what time is it?

No longer a need to wonder. The RM-II5 provides all this information on an easy to read front panel LCD meter. The meter reports volts, amps, watts, frequency, power factor, power consumption (KwH) and even time of day - valuable information in situations involving dynamic loads or questionable power quality. In addition, LEDs indicate power on, properly attached ground and continuing AC surge protection.

The RM-II5 is also a great power conditioner, providing 40,000 amps of surge protection and up to 60dB of AC line noise filtration. This product is particularly useful for rental or live sound systems where its value comes from a combination of protection and practical features.

Ten outlets on the back and two on the front. Includes switch cover to prevent accidental turn on or off. Comes with 15 foot power cord. Also available in 20 amp (RM-I2O).

SPECIFICATIONS

Rated Voltage I20VAC
Rated Current RM-II5: I5A, RM-I20: 20A

Peak Surge Current 40kA (20kA per mode)

Response Time < 5ns

Surge Protection Thermal Protected MOVs

EMI RFI Filtration < 60dB

Power Cord (I5 ft) RM-II5 I4/3 with NEMA 5-I5P RM-I20 I2/3 with NEMA 5-20P

Output Receptacles RM-II5 NEMA 5-ISR Front (2), Back (IO)
RM-I20 NEMA 5-20R Front (2), Back (IO)

LED Status Indication Power, Ground, Surge Protection

Meter Reading Volts, Amps, Watts, VA, Hz, PF, KWH, Time of Day

Dimensions 1.75" x 19" x 5.0"

Warranty I Year



For additional information or to place an order p: 713.772.1404 f: 713.772.7360 e: info@juicegoose www.juicegoose.com