

### Cables to Connector Cross-Reference

#### ■ BNC, F, RCA, etc.

See page 43, for more information about the crimp height.

Model	BNC							F	RCA	Others	Suitable Die Set (*1)	Crimp Height
	Crimp Plug				Solder Plug	Jack	FP-C					
	BCP-B	BCP-A	BCP-C	MBCP-C	BCP-LC	BCP-H						
L-1.5C2VS/V*-1.5C			BCP-C1								TCD-1DB	—
1.5C-2V							BCJ-FC1(-7/16) BCJ-RUC1					
L-2.5C2V		BCP-A25									TCD-35CA	1.40 - 1.47
L-2.5CFB		BCP-A25F		MBCP-C25F					RCAP-C25F			
1855A	BCP-B26											
1855P												
L-2.5CHD/L-2.5CHLT	BCP-B25HD							FP-C25HD	RCAP-C25HD			
VDM230												
1855ENH	BCP-B28											
HD PRO 0.6/2.8 AF												
1506A		BCP-A32										
V4-2.5CHW	BCP-B25HW											
L-3C2V/L-3C2VS		BCP-A3			BCP-LC3	BCP-H3B BCP-H5/1		FP-C3	RCAP-C3A	MCM-V5C3 MCF-V5C3		
V3-3C/V4-3C		BCP-A3										
V5-3C		BCP-VA3								MCM-V5C3 MCF-V5C3		
L-3CFB	BCP-B3F	BCP-A3F		MBCP-C3F	BCP-LC3F	BCP-H3B BCP-H5/1		FP-C3F	RCAP-C3F			
V*-3CFB												
1695A		BCP-A55						FP-C55A				
VSD2001TS												
L-3C2W		BCP-A31						FP-C31			TCD-31C	
L-3CFW	BCP-B31F					BCP-H31F						
V*-3CFW												
LV-61S		BCP-A4		MBCP-C4			BCJ-C4	FP-C4	RCAP-C4A	VWP-C4A MVP-C4	TCD-4CA or TCD-451CA	1.40 - 1.50
RG-59B/U												
L-4CFB/V*-4CFB	BCP-B4F	BCP-A4F		MBCP-C4F				FP-C4F	RCAP-C4F			
1505A, 1505ANH												
HD PRO 0.8/3.7 AF												
VPM2000												
L-4CHD		BCP-A42							RCAP-C42		TCD-31C	
1505F												
L-4.5CHD	BCP-B53			MBCP-C53				FP-C53A	RCAP-C53			
1694A												
HD PRO 1.0/4.8 AF	BCP-B56											
L-4.5CHWS	BCP-B45HW					BCP-H45HW					TCD-35CA	
L-5C2V/L-5C2VS		BCP-A5			BCP-LC5	BCP-H5B BCP-H5/1		FP-C5	RCAP-C5A			
V*-5C		BCP-A5 BCP-VA5										
LV-77S		BCP-A77							RCAP-C77			
L-5CFB	BCP-B5F	BCP-A5F (*2)		MBCP-C5F	BCP-LC5F	BCP-H5B BCP-H5/1 BCP-H51F		FP-C5F	RCAP-C5F		TCD-5CF or TCD-55FA excluding BCP-A5F (*2)	
V*-5CFB												
L-5CFW	BCP-B51F					BCP-H51F						
V*-5CFW												
8281F		BCP-A77							RCAP-C77			
L-5C2W		BCP-A52						FP-C52			TCD-451CA	
L-5CHD			BCP-C5HD								TCD-5HD	1.90 - 2.00
L-6CHD			BCP-C6HD								TCD-67HD	2.15 - 2.25
L-7CHD			BCP-C7HD									
L-7CFB			BCP-C7FA					FP-C7FA				
7731A			BCP-C71A								TCD-7CA	1.90 - 2.00
9292								FP-C71A				
L-8CHD										NCP-H8HD	—	—
GS-6									RCAP-C3GS		TCD-35D	2.01 - 2.20

#### ■ DIN 1.0/2.3, 4K-DIN

Model	DIN	4K-DIN	Suitable Die Set	Crimp height
	DCP-C	MD		
L-2.5CHD/L-2.5CHLT	DCP-C25HD		TCD-D253F	1.08 - 1.16
1855A				
VDM230				
V4-2.5CHW		MDM-V4C25HW MDF-V4C25HW		
L-3CFB	DCP-C3F			
L-4CFB	DCP-C4F		TCD-D534F	1.25 - 1.33
1505A				
VPM2000				
L-4.5CHD				
1694A	DCP-C53			
VSD2001				

\*1: Die set is not required for BCP-H series and NCP-H8HD \*2: Suitable die set for BCP-A5F is TCD-35CA  
See page 40-41, for 50 ohm cables and connectors.

Belden: 1505A, 1505ANH, 1505F, 1506A, 1694A, 1695A, 1855A, 1855ENH, 1855P, 7731A, 8281F, 9292  
Draka: HD PRO 0.6/2.8 AF, HD PRO 0.8/3.7 AF, HD PRO 1.0/4.8 AF  
Gecco: VDM230, VPM2000, VSD2001, VSD2001TS

Note: Be sure to use the right combination of cable, connector and die set for proper connection