



CYBER PAK™

SKU# CYBER PAK

The CYBER PAK™ is an all-in-one Dimmer/Power/MIDI Pack with multiple functions. This pack allows you to convert from a dimmer to a relay pack through the menu function.



FEATURES

- (4) Channel Dimmer/Relay/MIDI Pack
- Individual DMX Address for each Channel
- Selectable Modes (Dimmer or Switch Pack)
- (16) Internal Chase Macros with Fade In/Out
- DMX Fail (loss of signal) Settings: HOLD/OFF/ON
- Power Failure Memory

DIMMER MODE:

- (4) Channel Dimmer (1, 2 or 4 Channel Option)
- Individual Channel Assignment & Output Limiter

RELAY MODE:

- (4) Channel Relay (1, 2 or 4 Channel Option)
- Individual Channel Assignment

CHASER MODE:

- (4) Channel Chase Controller
- 16 Internal Chase Programs
- Adjustable Fade Times

MIDI MODE:

- Receives MIDI Notes 001-128 Program
- MIDI In & MIDI Through Connections

Specifications subject to change without notice ©Elation Professional 10/01/18

Elation Professional USA | 6122 S. Eastern Ave. | Los Angeles, CA. 90040
323-582-3322 | 323-832-9142 fax | www.elationlighting.com | info@elationlighting.com

CONTROL / CONNECTIONS

- (2) 3-prong Edison Sockets per Channel (8 total)
- 5pin MIDI IN/OUT Ports
- 3pin XLR IN/OUT Ports
- (4) Button LED Display Control Panel
- Master Power Switch

SIZE / WEIGHT

- Length: 8.3" (212mm)
- Width: 10.4" (265mm)
- Vertical Height: 3.0" (75mm)
- Weight: 8.0 lbs. (3.6kg)

ELECTRICAL / THERMAL

- AC 120V 50/60Hz 20A Max
- 2,400W Max Power Consumption (600W per channel)

NOTE: Main Power Cord is Bare Wire, 3-Prong Connector Not Included

APPROVALS / RATINGS

CE | cETLus



Elation Professional B.V. | Junostraat 2 | 6468 EW Kerkrade, The Netherlands
+31 45 546 85 66 | +31 45 546 85 96 fax | www.elationlighting.eu | info@elationlighting.eu