



Mini-Connect

The AJA Mini-Connect device enables control of up to 4 USB-enabled AJA ROI Mini-Converters over a single Ethernet connection. Mini-Connect integrates with your existing Ethernet network to provide access using any web browser for easy configuration and control of ROI Mini-Converters anywhere in your facility.

\$345 US MSRP

<https://www.aja.com/products/mini-connect>

Supported AJA Mini-Converters

- ROI
- ROI-DVI
- ROI-HDMI
- ROI-DP
- Others TBD*

*NOTE: Future Software Release

Network Interface

- 10/100/1000 Ethernet (RJ-45)
- Embedded web server for remote control via Mini-Connect
- Configuration and transport control via web interface

USB Configuration

- Configuration and device control via web based UI

USB (interface with ROI converters)

- Connect up to 4 ROI Mini-Converters for control via Ethernet

User Interface

- Web based UI running Mini-Connect software

Size (w x d x h)

- 4.6" x 2.4" x 1.0" (109mm x 78mm x 25mm)

Power

- Uses AJA power supply model DWP-U-R1, included with purchase
- 100-240V, 50/60 Hz Universal Input
- +5 to 20V DC regulated, 8 watts max

Environment

- Safe Operating Temperature: 0 to 40 degrees C (32 to 104 degrees F)
- Safe Storage Temperature (Power OFF): -40 to 60 degrees C (-40 to 140 degrees F)
- Operating Relative Humidity: 10-90% noncondensing
- Operating Altitude: <3,000 meters (<10,000 feet)