



PRELIMINARY PRODUCT INFORMATION  
JUNE 2000

ISM-3 Release date July 2000



#### Description

The ISM-3 (Input Signal Mixer) is an active direct input box which features 6 line inputs (3 RCA, 3 TRS) and 3 outputs (1 RCA, 1 TRS, 1 XLR) .

#### Applications

The ISM-3, also called the "Session Box," was designed primarily for Hip-hop/turntablist DJ teams. In most cases, when DJs scratch together in a team, the performance mixers are daisy-chained together from one mixer to the next using one of the mixer's line inputs. With the ISM-3, the DJ can connect up to six mixers together without losing input channels on their mixers.

The ISM-3, however, can be used for various other applications. It is especially handy where a mixer does not feature balanced outputs.

The ISM-3 is a DJ focus concept developed by Stanton.

Line inputs: 3 (RCA), 150 mV / 27K ohm, 3(TRS 1/4") 775 mV / 1K ohm • Master output: 1 (XLR; 1/4" TRS; RCA unbalanced), 775 mV / 1K ohm • Record output: 1 (RCA), 245 mV / 10K ohm • Frequency Response: 20 Hz - 20 kHz, +/- 2 dB • S/N Ratio: Less than 70dB • T.H.D: less than 0.2% • Dimension(LxWxD): (350 x140 x 83 mm) • Weight: 3.3 lbs (1.5 Kg)

STANTON MAGNETICS, LLC  
2821 Evans St. Hollywood, FL 33020 - (954) 929-8999  
Fax: (954) 929-0333 - [info@stantonmagnetics.com](mailto:info@stantonmagnetics.com)  
[www.stantonmagnetics.com](http://www.stantonmagnetics.com)