



## S 220 Portable 2-Channel Infrared System

The S220 is a portable, two-channel infrared system with the ability to change modes of operation, from single channel transmission (12,500 square ft coverage) to two channel operation (6,250 square ft coverage), at the flick of a switch. Two-step installation merely requires the connection of a microphone, tape recorder, or similar audio source and 110 V AC. Once turned on, the S 220 is ready to transmit.

Slave emitters can be daisy chained for additional coverage. It has two microphone and two line-level inputs as well as two line-level outputs. These outputs allow the S 220's input signals to be fed through the unit to a house PA system or a tape recorder (i.e. for taking minutes).

Setup is extremely easy, making it a natural for schools, courtrooms, and hotel conference/convention rooms. The SC110, soft carrying case, protects the S 220 during transport and can store microphones and cable.

### Features—Benefits

- New, higher sub-carrier frequencies to avoid interference from fluorescent lighting
- Barrier strip for easy installation
- Cost effective for areas up to 4,000 sq. ft.
- DC loop-through and daisy-chain capabilities
- Available in black
- 1-year warranty
- Greater coverage area
- Convenient interconnectivity
- Controlled from a single location
- Ease of installation
- Excellent reliability

### Technical Data

Subcarrier frequency	95 and/or 250 kHz selectable or stereo
Transmission area	12,500/6,250 sq. ft.: single/two channel
Inputs	2 x XLR balance mic level 2 x 1/4" Line level
Outputs	2 x 1/4" Line level
Power requirements	110 V AC
Dimensions in inches	13.25 x 9 x 6.5
Weight	11 lbs. 8 oz

### Product Variants

SZI 1015T/NT SZI 1015T with NT 1015-120 power supply

SZI 1015T-W SZI 1015T in white (no power supply)

SZI 1015T-W/NT SZI 1015T in white with NT 1015-120 power supply

## Optional Accessories

---

Floor stand	SEMS 3000
Power supply	NT 1015-120
Charger for one BA 90	L90-120
Charger for 10 BA 90's	L 92-10/NT
Charger for 20 BA 90's	L 92-20/NT
BA 90 and carrying case	HC101

### Recommended Receivers

RI 100 S Single channel, stethophone receiver with BA 90 rechargeable battery

RI 100-J Same as RI 100 A but with 1/8" mono jack for connecting with hearing aid accessories