

P-30FA

30 Watt PA Amplifier with Digital AM/FM Tuner



Our professional 30 Watt PA amplifier features a digital 30 station preset FM/AM tuner, built-in telephone paging, voice activated priority paging and music on hold circuits. Input connections include two locking Cannon type XLR connectors, one 1/4" microphone connector, one RCA aux input. Outputs include 4 ohm, 8 ohm, and 25/70 volt. It has a 30 Watt RMS at less than 1.0% distortion. It has a dual voltage 120V/220V AC for 50/60 Hz. A rack mounting kit is included.

Specifications

Inputs	2-Mic Inputs: XLR Connectors, Hi or Lo Z, Balanced 1 Aux Input: RCA Connector, 1 Tel Paging 1 Equalizer: 1/4" Audio
Outputs	4 & 8 Ohm, 25 & 70V line
Controls	2-Mic Controls, 1-Aux Control Separate Bass and Treble Controls Master Volume Control, Tuner Control ON/OFF Power
Sensitivity	Mic 1mV, Aux 100mV Tel 200mV/600 Ohm
Noise	Mic 70 dB, Aux 80 dB FM 60dB - AM 50 dB
Frequency Response	30-20,000 Hz
Distortion @ Rated RMS	Less than 1%
Rack Mounting Kit	Included
Dimensions	3-3/4"(H) 6-1/2"(W) 11-1/2"(D)
Weight	14 lbs, 8 oz.

Specifications subject to change


speco technologies™



For more information contact us at:

Speco Technologies 200 New Highway, Amityville, NY 11701 Web: www.specotech.com
Toll Free: 1-800-645-5516 In Metro NY: 631-957-8700 Fax: 631-957-9142 or 631-957-3880