

## Digital Camera Hop Receiver



- Tunes across a wide UHF frequency range
- 256-bit encryption - AES 256-CTR
- AES3 and dual mic/line level analog outputs
- Headphone monitor output
- USB port for firmware updates
- Compatible with DCHT , M2T, M2T-X, and D2 Series transmitters (DBu, DHu, DPR)
- 2-way IR (infrared) port for fast setup
- 2 AA battery power
- Solid machined aluminum housing

The DCHR Digital Receiver is engineered to work alongside the DCHT transmitter to form the Digital Camera Hop system. The receiver is also compatible with the M2T unencrypted and M2T-X encrypted digital stereo transmitters, and the D2 Series mono digital transmitters, including the DBu, DHu, and DPR. Designed to be camera mountable and battery powered, the receiver is ideal for location sound and televised sports, along with many other applications. The DCHR employs advanced antenna diversity switching during digital packet headers for seamless audio. The receiver tunes across a wide UHF frequency range.

The headphone monitor output is fed from a high-quality stereo amplifier with power available to drive even inefficient headphones or earphones to sufficient levels for noisy environments. An intuitive interface and high resolution LCD on the unit provide users with a quick read on the status of the system.

The DCHR also employs 2-way IR sync, so settings from the receiver can be sent to a transmitter. This way, frequency planning and coordination can be done quickly and confidently with on-site RF information.

### DCHR Summary

The DCHR operates in the UHF frequencies of 470.100 to - 607.950 MHz in a single range for maxi-

mum flexibility. The Locale setting is used to restrict the tuning range for North American users to an upper limit of 607.375 MHz.

The receiver employs AES 256-bit, CTR mode encryption for robust security, and four key management policy choices for different applications.

Housings and panels are made of machined aluminum with **ebENi** finishes (black electroless nickel plating) with laser etched marking for durability, yet they are lightweight and sleek in order to occupy minimal space on a camera. The DCHR features a user-friendly interface with a high-resolution, backlit LCD and membrane switches for ease of setup and system monitoring.

The DCHR runs for 8 hours on two lithium AA batteries.



## Specifications



<b>Operating Frequencies:</b>	US: 470.100 - 607.950 MHz
<b>Modulation Type:</b>	8PSK with Forward Error Correction
<b>Audio Performance:</b>	
<b>Frequency Response:</b>	D2 mode: 25 Hz - 20 kHz, +0/-3dB Stereo modes: 20 Hz - 12 kHz, +0/-3dB
<b>THD+N:</b>	0.05% (1kHz @ -10 dBFS)
<b>Dynamic Range:</b>	>95 dB weighted
<b>Adjacent Channel Isolation</b>	>85dB
<b>Diversity Type:</b>	Switched antenna, during packet headers
<b>Audio Output:</b>	
<b>Analog:</b>	2 balanced outputs
<b>AES3:</b>	2 channels, 48 kHz sample rate
<b>Headphone Monitor:</b>	3.5 mm TRS jack
<b>Level (line level analog):</b>	-50 to +5dBu
<b>Latency:</b>	D2 mode: 1.4 ms Stereo modes: 1.6 ms
<b>Power requirements:</b>	2 x AA batteries (3.0V)
<b>Battery life:</b>	8 hours; (2) Lithium AA
<b>Power consumption:</b>	1 W
<b>Dimensions:</b>	Height: 3.0 in. / 72 mm.  Width: 2.375 in. / 60 mm.  Depth: .625 in. / 16 mm.
<b>Weight:</b>	9.14 ounces / 259 grams (with batteries)

*Specifications subject to change without notice.*



581 Laser Road NE • Rio Rancho, NM 87124 USA • [www.lectrosonics.com](http://www.lectrosonics.com)  
(505) 892-4501 • (800) 821-1121 • fax (505) 892-6243 • [sales@lectrosonics.com](mailto:sales@lectrosonics.com)