

Gold Line Connector, Inc.

Box 500 West Redding, CT. 06896

203-938-2588 phone - 203-938-8740 fax

<http://www.gold-line.com> Email: goldline@i84.net

Specifications For Model **FD23**

PRODUCT DESCRIPTION: 23 Channel Feedback Detector.

MICROPHONE: Built-in omnidirectional electret condenser.

MEASUREMENT FREQUENCIES (Hz): 80, 100, 125, 160, 200, 250, 315, 400, 500, 630, 800, 1k, 1.25k, 1.6k, 2k, 2.5k, 3.15k, 4k, 5k, 6.3k, 8k, 10k, 12.5k.

DISPLAY: Individual LED for each channel (23) measured.

POWER REQUIREMENTS: Batteries: Eight AA alkaline or nicad.

External: 12Vdc @ 200mA via 3.5mm jack. Tip positive.

SIZE (W x H x D); WEIGHT: 3¼" x 8" x 2¼"; 12 oz.

CASE MATERIAL: High impact ABS.

rev 8/27/96