



The Multi Mixer (JIB/MM) is an extremely versatile audio mixer designed to solve many of the patching and mixing problems that arise when connecting various devices together. It features a wide variety of input and output connectors including balanced XLR, balanced 1/4", stereo RCA, and stereo 1/8" to accommodate most of the cables found in pro and consumer audio situations. The MM also features a stereo Headphone output jack with a dedicated volume control to monitor the entire mix. The high gain/wide dynamic range design of the MM ensures that you will never have trouble matching levels between audio devices.

The MM will run off of 2AA batteries for about 15 hours or an optional DC power supply (JIB/US4.5-14). The MM will supply +24V phantom power to microphones. The MM is great for: 1) Adding inputs to an existing mixer by creating a sub-mix of two or more sources before sending the signals to the main mixer or powered speaker. 2) Serving as a sophisticated cable adapter that not only adapts the connector type but also provides the correct impedance with adjustable level control. 3) Serving as the main mixer for solo or duo acts as well as AV presentations. 4) As a mixer for rehearsals when it's impractical to set up the entire PA. 5) Interfacing pro audio gear with consumer audio gear. 6) Battery operation allows remote location use where AC power is unavailable. 7) As an emergency back-up mixer to have along just in case





- +24V Phantom Power
- 7 Input/4 Channel
- Headphone Output with Volume
- Multiple Outputs
- Metal Construction
- Portable - Runs off of 2 AA Batteries*
- High Gain/ Wide Dynamic Range



INPUTS:

CH 1&2: Balanced XLR/1/4" Combo w/ -20dB PAD and +24V Phantom Power

CH 3: Stereo RCA & 1/8" Mini

CH 4: Stereo RCA

OUTPUTS:

Stereo Headphone w/ Volume, Balanced XLR, Balanced 1/4", RCA - Stereo

Power: 2 AA Batteries (15 hours) or Optional AC Adaptor Part # JIB/UA4.5-14 (4.5 VDC 500mA minimum with 4mm barrel plug)

Weight: 2.25 Lbs.

*Operates on (2) AA Batteries or 4.5V power supply
Not included

UNIVERSAL POWER ADAPTER JIB-US4.5-14

Galaxy Audio is proud to introduce a new problem solver to its Audio Solutions line, the Universal Power Adapter. The JIB/UA4.5-14 supplies 4.5v DC, at 1A to many of the new products in our Jacks In The Box line as well as most CD and MP3 players using the common 4mm barrel plug with center positive. The UPA comes with 4 different AC plug adapters, and will accept any input voltage from 100 to 240v AC, 50-60Hz, which means it will work in nearly every country on the planet.



Specifications subject to change without notice.

GALAXY AUDIO

MAKERS OF THE ORIGINAL HOT SPOT PERSONAL MONITOR

601 E. Pawnee Wichita, KS 67211 316. 263.2852 FAX 316.263.0642 www.galaxyaudio.com

Distributed outside the United States by **E and E Exports, Inc.** 2815 Junipero Ave. Suite 101 Signal Hill, CA 92614
562.988.3447 FAX 562.989.3037

Distributed in Canada by **Audio Distributors International (ADI)** 1275 Newton, unit 6 Boucherville, QC J4B 5H2 Canada
450.449.8177 FAX 450.449.8180