Compact Dimming

- 6 Channels
- 1200 Watts per Channel
- 4800 Watts Total Power
- DMX-512 and LMX-128 Control
- Stand Alone Chaser Mode
- Relay Mode Switchable

AS-62D Compact Dimmer



SPECIFICATIONS

Channels: 6

Channel Capacity: 1200 Watts per Channel

Total Power: 4800 Watts

Control Protocol: DMX-512 and 3 Wire LMX-128

Control Connections: Dual 5 Pin XLR, DMX

Dual 3 Pin XLR, LMX

Power Requirements: 120VAC, Two 20 Amp Circuits

Power Input: Two Edison Plugs

Frequency: 50 or 60Hz

Fusing: 10 Amp each Channel

Preheat Voltage: Soft Start Control

Response Curve: Modified Square Law

Filter Rise Time: 350 Microseconds

Filter Max. Rate of Rise: 105 Milliamps / Microsecond

Response Time: 8.3 Milliseconds

Full Load Voltage Drop: 3 Volts

Conduction Angle Range: 180 Degrees

Efficiency: 97%

Size: 13.5"L x 8.5"W x 3 3/8"D

Weight: 8.5 Pounds

Architect & Engineer's Specifications

The dimming system shall have 6 circuits with a load capacity of 1200 Watts per circuit. Each circuit is protected by a 10 Amp fast acting magnetic circuit breaker or a 10 Amp fuse. An allowance of 200% overhead capacity is employed in the circuit design. The dimming system shall have a rise time of not less then 350 microseconds. Setup attributes of Dim or Relay, and unit address via the dipswitch controls. The dimming system shall use the USITT standard DMX-512 protocol for direct control of the dimming circuits and/or the Lightronics LMX analog multiplex protocol.

Power requirements of the dimming system shall be 120/208 VAC Single Phase or dual single ended operation, capacity shall be 20 Amps per leg. Load output connectors shall be a user selections of Edison or Stagepin style connector. Input electrical connections are made through 2 pigtails with connectors determined when purchased. The dimming system is to be mounted using standard lighting equipment clamps. Dimensions are $13.5^{\circ}\text{L} \times 8.5^{\circ}\text{W} \times 3 \ 3/8^{\circ}\text{D}$; the weight shall be 9 lbs. The dimming system is covered by a 5 year factory warranty.

The dimming system shall be a Lightronics AS-62D.

5 YEAR WARRANTY

The 5 year warranty is valid if the Warranty Registration card is returned to Lightronics, Inc. within 30 DAYS of the purchase date.

