

ME-1

NETWORKED PERSONAL MIXER

The ME-1 personal mixer is a small 40 channel mixer with a mono/stereo or headphone output.

The OLED display provides information about level, selected audio source, etc.

The ME-1 is connected by standard Cat5e Ethernet cabling and can be distributed thru standard IT hardware.

16 buttons provide a single audio channel or a group of audio channels.

The ME series can be used for audio distribution (break out rooms, translation, dressing rooms etc) or as a personal monitoring system for musicians.

The ME range is compatible with SQ, Qu, ME-U (Dante, Madi, etc) and the dLive series.



Key Features

- 40 Channel mixer
- POE / DC powered
- Ethernet L2 audio transport
- 16 Assignable keys
- Headphone or line output

Benefits

- Unlimited number on 1 network
- Preset recall / store on USB
- OLED display
- Group or single channel
- Solo mode