

MODEL	COLOR CODE	USE FOR	SIZING	MIN - MAX (In)	MIN - MAX (mm)	KRAMER'S CABLE
CON-COMP-BNC/M/RG-6	Green	BNC Compression Connector for RG-6 Cable.	Center Conductor	0.0399 - 0.0418	1.0135 - 1.0617	
CON-COMP-RCA/M/RG-6	Green	RCA Compression Connector for RG-6 Cable.				
CON-COMP-"F"/M/RG-6	Green	"F" Type Compression Connector for RG-6 Cable.	Dielectric	0.180 - 0.193	4.572 - 4.9022	BC-1X
CON-COMP-BNC/M/RA/RG-6	Green	Right Angle BNC Compression Connector for RG-6 Cable.				
CON-COMP-RCA/M/RA/RG-6	Green	Right Angle RCA Compression Connector for RG-6 Cable	Outer Jacket	0.265 - 0.305	6.731 - 7.747	
CON-COMP-BNC/M/RG-59	Red	BNC Compression Connector for RG-59 Cable.	Center Conductor	0.0317 - 0.0339	0.8052 - 0.8611	
CON-COMP-RCA/M/RG-59	Red	RCA Compression Connector for RG-59 Cable.				
CON-COMP-"F"/M/RG-59	Red	"F" Type Compression Connector for RG-59 Cable.	Dielectric	0.144 - 0.157	3.6576 - 3.9878	BC-1X59, BCP-1X59
CON-COMP-BNC/M/RA/RG-5	Red	Right Angle BNC Compression Connector for RG-59 Cable				
CON-COMP-RCA/M/RA/RG-59	Red	Right Angle RCA Compression Connector for RG-59 Cable	Outer Jacket	0.232 - 0.273	5.8928 - 6.9342	
CON-COMP-BNC/M/RG-179(26-28#)	Orange	BNC Compression Connector for Mini Coax Cable.	Center Conductor	0.015 - 0.025	0.381 - 0.635	BC-2X, BC-3X, BC-4X, BC-5X, BC-5X26, BC-5X5S, BC-3X2T7S, All BCP.*
CON-COMP-RCA/M/RG-179(26-28#)	Orange	RCA Compression Connector for Mini Coax Cable.				
CON-COMP-BNC/M/RA/RG-179(26-28#)	Orange	Right Angle BNC Compression Connector for Mini Coax Cable	Dielectric	0.065 - 0.078	1.651 - 1.9812	
CON-COMP-RCA/M/RA/RG-179(26-28#)	Orange	Right Angle RCA Compression Connector for Mini Coax Cable	Outer Jacket	0.095 - 0.160	2.413 - 4.064	
CON-COMP-BNC/M/22#	Purple	BNC Compression Connector for 22 AWG Cable.	Center Conductor	0.015 - 0.025	0.381 - 0.635	
			Dielectric	0.095 - 0.105	2.413 - 2.667	
CON-COMP-RCA/M/22#	Purple	RCA Compression Connector for 22 AWG Cable.	Outer Jacket	0.145 - 0.160	3.683 - 4.064	



KRAMER ELECTRONICS, Ltd.
3 Am VeOlamo St.
Jerusalem, Israel, 95463
Tel: + 972 732650200
Fax: + 972 2 653 5369
E-mail: info@kramerel.com
Web: www.kramerelectronics.com