



We Deliver the Power™

Lex Products Corporation
15 Progress Drive
Shelton, CT 06484
203.363.3738
203.363.3742 Fax

Lex West
11847 Sheldon Street
Sun Valley, CA 91352
818.768.4474
818.768.4040 Fax

www.lexproducts.com
info@lexproducts.com
800.643.4460

20 Amp Quad Box with PowerCON Input to Edisons, Feed Thru

PowerHOUSE™
Portable Distribution Boxes



Features & Benefits

- *Heavy-duty molded rubber enclosure is fully insulated and resistant to shock, impact and corrosion*
- *Compact and convenient way to place 20 Amp duplex receptacles where they are needed*
- *Feed thru option allows multiple boxes to be placed along the same feed*

Catalog Number: DB20PC-SBPC

Description:

20 Amp, Single Phase, 2 Pole, 3 Wire, 120 VAC, Quad Box Enclosure, PowerCON inlet to (2) NEMA 5-20, 20 Amp duplex receptacles, Feed Thru, NEMA 1 Indoor

Typical Application:

This extremely versatile box is used for placing convenient duplex receptacles exactly where they are needed. This box enables the user to create receptacle stringers using extensions of various lengths.

Markets Served:

Convention Centers, Live Events, Concert Touring, Industrial Maintenance and Repair

Specifications

Rating	20 Amp, Single Phase (H,N,G), 2 Pole, 3 Wire, 120 VAC
Environmental Rating	NEMA 1 Indoor
Input	(1) 20 Amp, 2 Pole, 3 Wire, 120 VAC, PowerCON inlet
Output	(2) NEMA 5-20, 20 Amp, 2 Pole, 3 Wire, 120 VAC duplex receptacles
Feed Thru	(1) 20 Amp, 2 Pole, 3 Wire, 120 VAC, PowerCON outlet
Overcurrent Protection	None
Dimensions	4.7"L x 2.5"W x 4.2"H
Approximate Weight	1.5 lbs.