







POSITIONING

Samson's Concert 99 wireless system combines 80 channels of high-definition audio and extreme reliability into a rugged all-metal, rack-mountable chassis with a stage-ready backlit display. With simple 1-touch setup, convenient monitoring, a 300' UHF operating range and impressive transmitter battery life this frequency-agile system offers an unprecedented value for performers and presenters.

FEATURES -

Simple Setup

In both single and multi-system arrangements, the CR99 Wireless Receiver offers 80 total operating channels, selecting the best frequency option for your area. Quick to setup, the CR99's Group scan helps avoid conflicting frequencies, while its IR sync function allows users to wirelessly match the transmitter to the receiver's operating frequency.

More Monitoring

The CR99 receiver features a bright, backlit LCD for monitoring on dark stages, even at long distances. The LCD also shows the exact battery life of your transmitter, along with the channel number and its corresponding UHF frequency.

Four Configurations

The Concert 99 Handheld features the CH99 Handheld Transmitter with Samson's Q8 professional dynamic mic capsule. The CB99 Beltpack Transmitter offers a sturdy metal clip and 1-touch Mute control. Beltpack transmitter configurations include Guitar (Samson GC32 cable), Earset (Samson SE10 earset mic) and Presentation (Samson LM10 lavalier mic). Concert 99 transmitters provide over eight hours of operation on two AA batteries.

APPLICATIONS

- Club-date musicians
- Wedding DJs and performers
- House of worship
- Education/corporate AV

SPECIFICATIONS

Concert 99 Wireless System

Working Range	300' (100m) line of sight
Dynamic Range	>103dB A-weighted
Signal To Noise	>90dB

CR99 Wireless Receiver

Audio Output Level	Balanced +9dBu, unbalanced +14dBu
Audio Output Impedance	Ralanced 2400 unhalanced 8100

CH99 Handheld Transmitter

Microphone Element	Samson Q8 dynamic
RF Power	10 mW EIRP
Battery Life	8 hours from 2 x AA batteries

Dattery Elic 0 Hours from 2 x 7/1/1 batteries		
CB99 Beltpack Transmitter		
Input Impedance	$1M\Omega$	
RF Power	10 mW EIRP	
Battery Life	8 hours from 2 x AA batteries	
Gift Box Dimensions (AII)	11.5" x 14.25" x 3.25" (293mm x 361mm x 85mm)	
Gift Box Weight (HH, BP)	4.5lb (2kg), 4lb (1.8kg)	
Master Carton Quantity (AII)	8	
UPC (US only)	HH: 809164211228, 809164211235 GTR: 809164211167, 809164211174 EAR: 809164211204, 809164211211	

PRES: SWC99BSE10-D, SWC99BSE10-K

samsontech.com

PRES: 809164211181, 809164211198