



**Configuration:**

LA-344 Replacement Mounting Hardware (For LT-84, LA-141 only)

**Product Overview:**

Easily mount and adjust your LT-84 ListenIR Transmitter/Radiator Combo and LA-141 ListenIR Expansion Radiator for any space or any installation with the LA-344 Replacement Mounting Hardware kit. The modular system allows the unit to be tilted 190° and rotated up to 360° with a locking ring to hold the desired position, and the included set screw adjusting options for a tamper-resistance setup. The length can also be adjusted to 2 in. (5.08 cm), 4 in. (10.16 cm), or 6 in. (15.24 cm) depending on the needs of your setup.

**Highlights:**

- Flexible, versatile mounting system for wall, ceiling, or table use
- 190° tilt adjustment and up to 360° rotation for any setup or installation
- 5.08 cm (2 in.), 10.16 cm (4 in.), or 15.24 cm (6 in.) length adjustment options

**Includes:**

- One (1) Wall Base
- One (1) Ceiling T-Bar Base
- One (1) Black Vinyl Base Cover
- Two (2) Shafts
- One (1) Adjustable Head with Locking Ring
- One (1) Alan Head Tamper Resistant Set Screw
- One (1) Alan Wrench
- One (1) 1/4 x 20 all-thread

Product Specification: Replacement Mounting Hardware (For LT-84, LA-141 only)	
Physical	
Shipping Weight	1.0 lbs (0.5 kg)
Base 2	T-Bar Clip for drop ceiling rails, 1/4-20 stud
Base 1	2" (50.8 mm) round base with four 0.188" (4.8mm) holes on 1.6" (40.6mm) bolt circle for solid surface mounting, 1/4-20 stud
Base Cover	Matching black vinyl cover adds a finished look to either base
Shafts	Two aluminum shafts, 0.5" (12.7mm) diameter, 2" (50.8mm) long, black, 1/4-20 stud
Adjustable Head	Fully adjustable with locking ring, 190° Tilt, 360° Turn and 360° Rotation)
Finished Lengths	2" (50.8mm), 4" (101.6mm) or 6" (152.4mm) long mount
Unit Weight	0.3 lbs (166.5g)
Maximum Load Weight	3 lbs (1.36 kg)