




0501, 0501.1 - ATTENUATORS



QC100 SHOWN

#### **GENERAL DESCRIPTION**

The Quam QC100xx is a dual gang, continuous rotary tenstep audio level attenuator with an OFF position.

The Quam QC101xx is a single gang, continuous rotary ten-step audio level attenuator with an OFF position.

Both single gang and dual gang formats are available in: -P (Priority relay), -RM (Rack Mount) and –W (White finish) formats described below.

All variants except the QC10xP are UL Listed 813.

Finish: QC10x, QC10xP- Brushed stainless steel, embossed position

 $QC10xRM-2" \times 2"$  dial scale, white on black QC10xW- White baked hybrid epoxy finish, no position on scale

Knob: QC10x, QC10xP, QC10xRM- Black with white indicator

# QC10xW– White molded indicator

### INTENDED USE

QC10x, QC10xRM, QC10xW:

Attenuates audio power to any number of loudspeakers up to 100W load. For use with 25V or 70.7V distributed audio systems, indoor environment. UL Listed 813

#### QC10xP: (No UL Listing)

Attenuates audio power to any number of loudspeakers up to 100W load. For use with 25V or 70.7V distributed audio systems, indoor environment. When internal 24VDC relay is activated, attenuator function is bypassed.

## **Quam-Nichols Company**

234 East Marquette Road, Chicago, IL 60637 Phone: (800) NEED NOW Fax: (888) NEED NOW (800) 633 - 3669 (888) 633 - 3669 E-Mail: neednow@qnc.com www.quamspeakers.com



# SYSTEM COMPONENTS

N/A

# RECOMMENDED ADDITIONAL QUAM COMPONENTS

0403– Surface Mounting Devices SE4W/2 Double Gang Box– QC100 Only SE4W Single Gang Box– QC101 Only

#### AUDIO SPECIFICATIONS

100W Continuous
Steps 1-2, -3 dB
Steps 3-10, -1.5 dB
OFF Position, -36 dB
< 0.5 dB

## **MECHANICAL SPECIFICATIONS**

Mounting	QC100, QC100W, QC100P: Dual Gang electrical box, 2-3/4" deep
	QC101, QC101W: Single Gang electrical box, 2-3/4" deep
	QC101P: Single Gang electrical box, 3-1/2" deep
	QC10xRM: 2RU rack panel or greater, 1/8" thick maximum
Relay Actuation	24VDC, 0.15A (QC100P only)
Audio Connection	10" long, color-coded tinned wires, pre-cut

Recommended construction sequences, installation instructions and A&E Specifications are available in various formats on the Quam Architects' and Engineers' Resources CD or on the web at: www.quamspeakers.com

© 2007 Quam-Nichols Company Quam-Nichols reserves the right to make changes and/or improvements to its products at any time and without notice.