MegaVox PRO PA System




Technical Specifications

Thousands report the MegaVox PRO as the most reliable Public Address system on the market. Emergency responders like its signal alert siren, wired microphone and convenient shoulder strap. Coaches, band directors and auctioneers appreciate the flexibility of the AC/DC operation and the range of the wireless microphones.

With the MegaVox Pro you're ready for any situation . . . it's lightweight, loud & easy to carry. Just grab it and go!





(MEGA-6000U2 Back Panel Shown)

MEGAVOX MODELS	
MEGA-7500	Battery powered PA system wired microphone & built-in rechargeable battery
MEGA-7500U1	One built-in wireless receiver
MEGA-7500U2	Two built-in wireless receivers

UHF WIRELESS

22 watts

transmitter

Wireless handheld microphone/

Wireless body-pack transmitter (requires handsfree microphone) Microphone options include:

Over-the-Ear/EM-TA4F, Lapel/LM-60,

Collar/CM-60, Headband/HBM-TA4F

CCESSORIES	
------------	--

A

MEGA-7501	Unpowered companion speaker
MIC-90P	Professional dynamic, cardioid pattern handheld microphone
SS-550	Heavy-duty speaker stand
NL-MEGA	Nylon storage cover
SOFT-TOTE	Nylon case with rollers & handle for speaker, stand & accessories
HC-1640	Traveling hard case
CC-550	Speaker stand bag for SS-550
RC-6000	MegaVox Charger
SC-50	50' Speaker cable for MEGA-6001

Anchor Audio, Inc.

Portable Sound Systems • Carlsbad, California

Features

True AC/DC, 110/220V power supply

22W AC/DC mode

126 dB of clear sound

Reaches crowds of 1.000+

Lightweight - Only 15 lbs

High-efficiency re-entrant horn driver

Powerful horn amplifier

Up to two built-in UHF wireless receivers

16-channel UHF diversity wireless receivers

Built-in rechargeable battery runs up to 10 hours on a charge

Microphone with coil cord


Signal alert button

External speaker output

External output powers optional MegaVox Pro companion speaker

Durable injection-molded case is tough, fade resistant & UV treated

Speaker stand receptacle molded into case bottom



TECHNICAL SPECIFICATIONS

Inputs

Line

Mic 1

Mic 2

Outputs

Speaker Out

Rated Power Output Max SPL @ Rated Power **Frequency Response** Charger (RC-6000) Battery Dimensions (HWD)

Weight

WH-6000

WB-6000

126 dB @ 1 meter 400 Hz - 10 kHz 18V DC/universal input (100Vac - 240Vac, 50 - 63Hz) 12 volt rechargeable, 5.4 AH 13"x 9" x 14" (33 x 23 x 36 cm) 15lbs / 6.8 Kg

Hi-Z, unbalanced, 1/4"-phone Lo-Z, unbalanced, 1/4"-phone (used for wireless on MEGA-6000U1) Lo-Z, unbalanced, 1/4"-phone Line (post fader) Lo-Z, 1/4"-phone 4Ω , unswitched, 1/4''-phone

(Features & Specifications Subject to Change Without Notice)

800.262.4671

www.anchoraudio.com S-MV/0810