



### TruLink<sup>®</sup> VGA to HDMI<sup>®</sup> Converter

- Maximum video output resolution of 1080p
- Video bandwidth: 1.65Gbps
- Converts an analog computer video signal to a HDMI video signal
- No software required

## Specifications: TruLink® VGA to HDMI® Converter

### Signal Specifications:

---

Input Signals:	Analogue Computer Video (RGBHV) Dual Channel Stereo Audio	
Output Signal:	HDMI	
Video Bandwidth:	1.65Gbps	
Supported Video Input Resolutions:	640 x 480	1280 x 768
	720 x 576	1280 x 960
	800 x 600	1280 x 1024
	1024 x 768	1360 x 765
	1280 x 720	1920 x 1080
Supported Output Video Resolutions:	480i	720p
	480p	1080i
	576i	1080p
	576p	
Audio Frequency Response:	20Hz to 20kHz	
Operating Frequency:	150MHz	

### Power Adapter Specifications:

---

Power Input:	100 - 240V~50/60Hz
Power Output:	5V, 1A
Pin Diameter	5.5mm
Center Pin Polarity:	Positive
DC Power Cable Length:	5.00ft

### Physical Characteristics:

---

Video Input Connector:	HD15 - VGA Female
Audio Input Connector:	3.5mm Stereo Audio Female
Video/Audio Output Connector:	HDMI Female
Housing Material:	Metal
Operating Temperature:	0° - 45°C
Storage Temperature:	-20° - 60°C
Weight:	1.10lb
Dimensions:	5.13 x 3.00 x 1.00in

---

Item Number	Description	Weight (lb)
40010	VGA to HDMI Converter	1.10

---