

ALL INCLUSIVE PORTABLE PA SYSTEM

The new TV5X is one of the latest models in the Traveler Series by Galaxy Audio. The Traveler Series is a line of powered speakers with built in batteries. All models in the Traveler Series can be run from either AC or the built in battery.

Most Traveler Series products are configurable to include built in CD/media players, UHF wireless microphones, Bluetooth receiver, or Audio Link Transmitter. Each item is built to order. Travelers are designed to be portable and used in a wide array of applications, like classrooms, churches, meeting rooms, graveside, auctions, among many others.

The TV5X has a built in 40 watt power amplifier with a 5" full range woofer and tone control. The TV5X, like other models in the Traveler Series, can be configured with up to two UHF wireless receivers or a Bluetooth receiver. Each UHF receiver has two different handheld mics and two body pack transmitters to choose from. There is also an optional MP3 player available which can play MP3s from USB or SD card.

The TV5X has a ¼" mic input with volume control, 1/8" input and output, and 4 bar battery level indicator. The built in Voice Priority, when activated, will lower the volume of the music when it receives a signal from a wireless or handheld microphone. This is convenient as you will not need to adjustment the volume of your music when needing to make announcements.


The TV5X is constructed from durable plastic and can be set on a table top, or on an optional tripod stand. The TV5i has a built in handle and shoulder strap for easy transport. The TV5X weighs 7lbs. An optional carrying bag is available.

- Built in Shoulder Strap
- 2 Wireless Microphones Optional
- One Wired Microphone Input
- Optional Bluetooth Receiver
- Optional Media Player
- Four-bar battery Indicator

















TV5X

Specifications

OPTIONS/SPECIFICATIONS

Sensitivity: 88 dB, 1 Watt @ 1 M

Maximum SPL: 104 dB

Frequency Response: 70 Hz ~ 16 kHz (audio)

Speakers: 5" Neolite Speaker

Receiver Module: AS-TVREC x 2 Diversity (optional)

Output Power: 40 W (RMS) @ 4ohm Signal to Noise Ratio: Up 70 dB

Optional Media Player: AS-DIGIMP5 (optional)

Audio Input: 1/4"-Mic. In, 1/8"-Aux In

Audio Output: 1/8"-Aux Out

Controls: Master, Tone, Aux In, Mic

Wireless Range: 150' (50 meters) to 220' (70 meters)

Power Supply: 20VDC 3.25A

Battery: 12V, 2.9Ah (Lead-Acid) Rechargeable Battery

Running Time: 4 ~ 5 Hours Charging Time: 3 ~ 4 Hours

Dimensions: 13.11" x 6" x 9.7" (333 x 153 x 246 mm)

Weight: 7 lbs (3.1 kg)



Optional Media Player and/or Wireless Mic Receiver up to 2

Master Control Panel with Battery Level, Mic input

Rechargeable Battery & Charger



AS-TVBPT

- Pendant Transmitter
- 96 Channels
- Lightweight Compact Size
- Soft Touch Buttons
- LCD Display
- Built in Microphone
- External Mic input
- Auxillary Line Input
- Two power settings 10 mW and 1mW
- Rechargeable Lithium Battery
- Single Charger Included
- Contacts for Optional Cradle Charger
- Removable Belt Clip

A5-TVMBP

- 96 Selectable Channels
- **Channel Selector**
- LCD Display
- Belt Clip
- 3-Bar Battery Condition Indicator
 - Mute Switch
 - Mic Input
- Aux Input
- Runs on 2 AA Batteries (14 hrs)
- 4.4 oz. (170g)
- Available with the HS-U3BK Headset or the LV-U3BK Lavalier



- 96 Channels
- Lightweight Compact Size
- Channel Up, Set & Down Selector
- Back Lit LCD Display
- Talk/Mute Soft Touch Button
- Two Power Settings 10mW, 1mW
- 150' Range
- Runs on Ž AA Batteries
- (about 12-16 hrs) **Charging Base** Terminals



A5-TVHH

- 96 Selectable Channels **Channel Selector**
- LCD Display
- Dynamic Capsule
- Built-in-Antenna
- 3-Bar Battery Condition Indicator
- Hi/Low Volume + Mute Switch
- Runs on 2 AA Batteries (14 hrs)
- DC Charging Input
- 8.3 oz. (280g)



Optional DC chargers



LV-U3BK

- Uni Directional Flement
- Freq. Response 50Hz - 19kHz



HS-U3BK

- Uni Directional Element
- Freq. Response 50Hz - 18kHz



AS-TVBPT & AS-TVH2



For AS-TVMBP

AS-DCBPTR



Control Panel Access



AS-TXRM

- 96 Selectable Channels
- Channel Selector
- RF and AF indicator
- Volume Control
- LCD Display
- Table Top/Rackmount Transmitter







*A Limited 90 Day Warranty Applies to Rechargeable Batteries Specifications subject to change without notice.

601 E. Pawnee Wichita, KS 67211 316. 263.2852 FAX 316.263.0642 www.galaxyaudio.com

Distributed outside the United States by **E and E Exports, Inc.** 2815 Junipero Ave. Suite 101Signal Hill, CA 92614 562.988.3447 FAX 562.989.3037 Distributed in Canada by **Audio Distributors International (ADI)** 1275 Newton, unit 6 Boucherville, QC J4B 5H2 Canada 450.449.8177 FAX 450.449.8180