Two Ch. Studio Microphone preamp

MP222







The new MP222 Studio Pro Preamp is a profesional two channel microphone preamp. Although having many possible uses, this microphone preamp was designed for studio applications. It has transformer balanced microphone inputs, true +48 Volt Phantom Power and many control options for getting your mic to sound just as you want it to when recording. It is great if you are just looking for studio quality mic processing, or any application where a high quality mic preamp is needed. With an Input Pad, +48 volt phantom power, level control, adjustable Phase, Low Cut filter and a mic-line switch for each channel. The MP222 is truely a studio grade profesional Mic Preamp.

Studio Pro Mic Preamp **Transformer balanced Inputs Dual Output 3.5mm Stereo** 5968 SOUTH 350 WEST S.L.C., UT 84107 PHONE: 801-263-9053

FAX: 801-236-9068

SPECIFICATIONS

Input Impedance: mic -Output Impedance: THD + Noise: S/N Ratio:

Frequency Response: Max Output Level:

Max Input Level: Max Gain: Current Draw:

Phantom Power: Input Connectors:

Output connectors:

Size: Weight: 600 Ohms or greater XLR 50 Ohms

.02% 110 dB

20 Hz - 30 kHz (+0 / -1 dB)

+14 dB +20 dB +70 dB

30 mA +48 VDC

4 Female XLR

1/8" (3.5mm) stereo out.

2 Male XLR 6.75"w x 5.125"d x 1.75" h

1.75 lbs.



Included - 15 VDC **ROLLS PS27s external** switching power supply







DATA SHEET FOR MP222 www.rolls.com MADE IN USA