



USB DMX Widget

Features

- Rugged Aluminum Housing
- Stackable- Yes
- Status LEDs for power and data in/out
- Fully Powered via USB Port
- Kensington Security Slot

- Platform- Hog 4 OS Family
- Input Connection- USB-B (1)
- Output Connection- 5-pin XLR (1)
- Control Output- DMX 512
- Output Channels- 512 (Total)

Universes-

Up to eight (8) DMX Widgets may be connected at once via a USB Hub to provide 8 full universes of DMX 512 to the Hog 4, Full Boar 4 and Hog 4 PC.

Four (4) DMX Widgets can be connected to the Road Hog 4, and HedgeHog 4X.

Two (2) DMX Widgets can be connected HedgeHog 4, Hedgehog 4S and HedgeHog 4N.



Weight- .34 Kg (.75 Lbs.)

Shipping Weight- .91 Kg (2 Lbs.)

Box Dimensions- (L x W x H)

229 mm (9 in.) x 127 mm (5 in.) x 178 mm (7 in.)

Storage Temperature- 20 - 60 c° (0 - 140 F) °

HES PN- 74040007

Dimensions / Physical

