

A-16CS Control Surface



The A-16CS Control Surface is designed to be an optional remote controller for the rack mounted A-16R Personal Mixer. The A-16CS plugs into an accessory port on the rear panel of the A-16R. A proprietary communication protocol, called A-Control, is used to send control information from the A-16CS to its host. The A-16CS connects to the A-16R via the same Category 5 cables used elsewhere in the A-16 Personal Monitor Mixing System™.

The A-16CS Control Surface allows users to adjust all the settings of the rack mounted A-16R Personal Mixer from a remote location. Functions include Channel level and pan, Groups, Solo and Mute functions. It uses the same familiar button layout as the A-16 Personal Mixer. In addition, the A-16CS allows the user to remotely save and recall Presets.

The rear panel of the A-16CS includes a footswitch jack which is used to step through the sixteen saved Preset mixes. Any dual foot pedal, such as those used with keyboards, can be used to perform the Preset up/down function.

A-16CS Features:

- Sixteen channel select buttons with dual LEDs
- Dedicated Recall, Group, Solo, and Mute buttons
- Sixteen user preset memory locations
- Pan/Spread control with LED readout
- Channel volume control with LED level readout
- Master Volume, Treble and Bass controls
- Footswitch jack for Preset up/down control
- Tabletop or mic stand mountable (using optional MT-1 mounting bracket)

A-16CS Control Surface Specifications

A-Control Inputs	1	Category 5 (RJ45 connector)
Footswitch Input	1	TRS ¼" dual function
Size	10.75" wide x 5.6" deep	2.22" high
Weight	3.4 lbs	
Options	MT-1	Mic stand mounting bracket