



4-Way Splitter/Combiner

Channel Vision's HS-4 splitter/combiner allows 4-way combining or splitting of TV antenna or cable signals. This splitter is DC passive allowing passage of low-voltage signals along the coax cable.



FEATURES

4-Way Splitter / Combiner

1Ghz, DC pass all port

Bulk-pack poly bag

7.5dB Insertion Loss

Machine threads

Grounding Screw

SPECIFICATIONS *

*Specifications subject to change.

Bandwidth: 5 - 1000MHz

Insertion Loss: 7.5dB

Max Insertion Loss: 1GHz = 8.5dB

RFI Isolation: -120dB

Return Loss: >16dB

Out to out isolation: >18.5dB

DC resistance Output to IN: <.1ohms

Input/Output Connectors: F type female

Max DC pass thru current: 500mA

