



SEVENTY-TWO

ADVANCED CONTROL PERFORMANCE MIXER

Solid steel construction

(3) New MAG THREE contactless tension-adjustable faders for crossfader and channel faders with reverse, contour controls, and cut-in adjustment

4.3-inch touchscreen for moving-wave display, X/Y FX control, song selection and user customisations

Dual FLEX FX engines

Dual die-cast aluminum FX paddles with 180-degree rotation

Chain-integrated Serato software effect control plus one internal FLEX effect per channel

11 Flex FX effects – also XY controllable

SEVENTY-TWO

Premium 2-channel mixer with multi-touch screen for pro DJs and turntablists

The RANE DJ SEVENTY-TWO is a 2-channel, advanced control and performance mixer, addressing the creative power of Serato DJ Pro software. Featuring a full color touchscreen interface, stackable Serato and Flex FX, plus the ultimate in expressive playback control via eight multi-function trigger pads, the RANE SEVENTY-TWO redefines the scope and possibilities for Pro, Club and Scratch DJ/Turntablists.

With the strength and durability of solid-steel and aluminum casing, the gig and battle-ready SEVENTY-TWO mixer represents the ultimate in advanced control needs and performance expectations of today's DJs. Designed in collaboration with leading Turntablists around the world and with the foundation of a globally trusted Seattle, US based engineering heritage, the SEVENTY-TWO redefines what is possible when true DJ artistry meets ground-breaking technology.

Powered by the all-new Serato DJ Pro software, the SEVENTY-TWO's 4.3-inch color touch-screen interface visualises its moving waveforms, enabling navigation, track selection and extensive performance preference adjustment too. It also offers full FX control and sonic manipulation utilizing and stacking the SEVENTY-TWO's dual Flex FX engines with Serato DJ Pro's extensive effects banks. Two DJ's can perform simultaneously and handover effortlessly via the unit's dual-USB connections. Turntablists can cut, flare, chirp, crab, orbit and transform with the new, tactile and precision based Mag Three faders, then flip between creative control functions via the 16 MPC-style pads with RGB backlight and multi-performance mode selections. Also, Serato's expressive Pitch 'n Time DJ expansion is included free with the SEVENTY-TWO, for DJs to integrate creative 'pitch-play' techniques into the mix.

Product Features

- Solid steel construction—built like a tank for non-stop, heavy-duty use
- (3) New MAG THREE contactless tension-adjustable faders for crossfader and channel faders with reverse, contour controls, and cut-in adjustment
- 4.3-inch touchscreen for moving-wave display, X/Y FX control, song selection and user customizations

- Dual FLEX FX engines, one for each channel
- Stacked Serato DJ Pro FX with internal post-fader FLEX FX
- Dual die-cast aluminum FX paddles with 180-degree rotation
- Chain-integrated Serato software effect control plus one internal FLEX effect per channel
- 11 Flex FX effects – also XY controllable (Echo, Hold Echo, Duck Echo, Reverb, Filter, Phaser, Auto Gate, Flanger, Delay, Ping Pong Delay, Beat-Breaker)
- Four Pad FX (Echo, Brake, Reverse, Gate)
- Full control over Single and Gang Serato FX
- Mic Echo
- Foot Switch control option
- 14 Pad Modes (Cue, Pitch Play, Auto Loop, Manual Loop, Roll, Pad FX, Sampler, Fader FX, Flip (requires purchase of Serato Flip expansion), Slicer, Transport, Slicer Loop, Flip, 3 Custom Pad Sets)
- Dual USB connections for DJ handoffs and simultaneous performance
- Legacy RANE US engineered superior, class-leading audio quality (114db SNR USB to analogue output)
- 16 Akai Pro MPC performance pads w/RGB backlight, adjustable threshold and aftertouch, with independent mode controls per deck.
- Industry first – assignable USB controller inputs for RANE TWELVE motorised control turntable
- Full on-board Serato DJ Pro transport/pad control should traditional turntables fail
- Unlocks Serato DVS, with Serato's Official Control Vinyl included (also ships with Serato Pitch 'n Time DJ expansion)

What's New in 1.3.2?

Improved Flex FX knob response

What's New in 1.3?

The new release delivers several new key features and improvements, including the highly sought-after Serato post-fader software effects, improved trigger response times and additional information on the SEVENTY-TWO's heads-up display. The Serato DJ software release will offer additional features such as a new expansion pack 'Serato Play' and support for multiple music streaming services.

New/Updated Features of SEVENTY-TWO 1.3:

- Added support for Serato Post Fader FX
- Improved pad response time and overall performance
- Track end warning now displayed on waveform screen
- Addressed a potential issue that the waveform screen might freeze.
- Quick Auto-Loop triggers have been added to FX Encoder control while in waveform view
- Add 3/4 time parameter to ECHO FX
- Added Cue and sample names to heads up display
- Improved settings menu workflow
- Improved BPM alignment between SEVENTY-TWO and Serato
- Added Fader calibration reset in RANE control application
- Various other improvements
- Added midi output for SHIFT + BROWSE knob pressed & BACK button
- Added Fader start (SHIFT +)

Web Copy/Short Descriptor for product in category or site search result page

Premium 2-channel mixer with multi-touch screen for pro DJs and turntablists.

Technical Specifications for product pages

Display: Full-color display with capacitive multi-touch (2.1" x 3.7" / 54 x 95mm (w x d)) (4.3" / 109mm (diagonal)) Pads: 16x velocity-sensitive multi-color back-lit pads (8 per deck, 10 modes each)

Faders: 3x MAG THREE magnetic design, tension-adjustable contactless faders (2 channel/line faders, 1 crossfader)

Outputs:

2x XLR (Main)

2x ¼" (6.35mm) TRS (Booth)

1x RCA stereo pair (Session)

1x ¼" (6.35mm) TRS (Headphones) 1x ⅜" (3.5mm) TRS (Headphones)

Inputs:

4x RCA stereo pairs (Deck 1–2)

2x XLR / ¼" (6.35mm) TRS (Mic 1–2) 1x RCA stereo pair (Session)

1x ¼" (6.35mm) TRS (Footswitch)

Connections:

2x USB Type-A ports (Deck 1–2 USB Controllers) 2x USB Type-B ports

1x IEC power cable input

Digital Audio

Converters: AKM High Definition Audio; 24-bit PCM, 48kHz Digital Signal Processing: 32-bit, floating point, double precision

Dynamic Range (A-weighted, unity gain): ADC: 114dB

DAC: 114dB

CD Input to Analog Output: 114dB CD Input to USB Output: 114dB

USB Input to Analog Output: 114dB

Power

Voltage: 100–240V, 50/60Hz

Consumption: 30W

Dimensions (w x d x h): 11.2" x 17.5" x 4.25" (28.4 x 44.5 x 10.8cm)

Weight: 12.0 lbs. (5.46kg)

RANE DJ - approved #hashtags

The hashtags listed below are RANE DJ approved for use across Social Media channels such as Instagram, Facebook and Twitter and will be supported with targeted SEO/marketing campaigns to increase web traffic and visibility to partner channels utilising them.

#reclaimthebass #RANEvolutionary #RANEseventytwo #RANEtwelve #controlperformance #RANEdj #serato #seratodjpro #needleless #notonearm #turntable #turntablist #battleready #RANEdjs

Overview Video

The current video providing an overview of the SEVENTY-TWO can be found on YouTube, using the URL below:

<https://youtu.be/-GokeAGyvQg>