## **Multiplexers and Band Separators/Combiners**

DSV Series, ZHLSJ, ZUVSJ



Blonder Tongue's multiplexers are designed to combine or separate the various bands of frequencies used in RF distribution systems.

Several models are available, including: VHF LB & VHF HB split, VHF & UHF split, and sub-band & CATVsplit. The compact passive units exhibit low insertion loss and high isolation.

### **O DSV Specifications Notes**

- (a) 50 to 550 MHz (b) 5 to 30 MHz (c) 54 to 860 MHz (d) DC 42 MHz
- (f) 45 to 50 to MHz (g) 30 to 35 MHz
- (h) 860 1000 MHz (j) 550 to 1000 MHz
- (e) at 50 MHz

### O Features & Benefits

- Models Available in VHF Low/Highband, VHF/UHF and Sub/CATV
- Low Insertion Loss
- Superior Isolation
- Compact Housings

C	<b>Specifications</b>
---	-----------------------

Electrical	DSV		DSV-42	
Band Separation (MHz):	5-30	50-1000	DC-42	54-1000
Insertion Loss (dB):	0.5	1.0	0.5	1.0
Isolation (dB):	55 (a) 45 (f) 45 (j)	55 (b) 45 (g)	55 (c) 45 (h)	55 (d)
Impedance (Ohm):	75	75	75	75
Return Loss (dB):	14	14	14	14
General				
Power Passing Capability (A):	0.5	-	0.5	_
Mechanical				
Dimensions LxWxD:				
(in)	7.38 x 1.69 x 1.00		7.38 x 1.0	69 x 1.00
(mm)	187x51x44		187x51x44	
Weight:	_		_	
(oz)	7.1		7.1	
(gr)	201		201	
Connectors				
RF Inputs/Outputs: "F" type, female		e, female	"F" type	, female



# **ZHLSJ**Band Separator Low/High Band

## Specifications ZHLSJ

Bandwidth	
Low: High:	DC to 108 MHz 175 to 216 MHz
Low Band Rejection (54-108 MHz):	22 (Min.) dB
High Band Rejection (174-216 MHz):	20 (Min.) dB
Insertion Loss:	0.5 dB
Impedance:	75 Ohm
Power Passive:	Low band only



## **ZUVSJ**Band Separator/ Combiner UHF/VHF

Specifications	ZUVSJ
Bandwidth	
VHF:	DC to 250 MHz
UHF:	470 to 890 MHz
VHF Band Rejection:	23 (Min.) dB
UHF Band Rejection:	30 (Min.) dB
Insertion Loss:	0.5 dB
Impedance:	75 Ohm
Power Passive:	VHF band only

#### O Ordering Information

Model	Stock No.	Description
DSV-42	4376	Band Separator DC-42/54-1000 MHz Split
DSV	4375	Band Separator 5-30/50-1000 MHz Split
ZHLSJ	1977	Band Separator/Combiner Low & FM/ High
ZUVSI	1978	Band Separator/Combiner UHF/VHF