



Product Overview:

LA-112 RG-58 50 Ohm Coaxial Cable is measured and cut per foot. It is best used when more distance is needed for the antennas to have better coverage. Recommended for coaxial runs less than 100 ft. (30.5 m) at 72 MHz or 50 ft. (15.24 m) at 216 MHz. The LA-112 minimum order is 20 ft. (6.1 m). Signal loss for 72 MHz is 2 dB per 50 ft. Signal loss for 216 MHz is 4 dB per 50 ft.

Highlights:

- Furthers antenna location
- Longer cable runs with low gain loss
- Cut to custom length with no connectors

Includes:

LA-112 RG-58 50 Ohm Coaxial Cable (Per ft.) (minimum of 20 ft.)

Product Specification: RG-58 50 Ohm Coaxial Cable (Per ft.)	
Interconnections	
Attenuation	2 dB per 50 ft. on 72 MHz, 4 dB per 50 ft. on 216 MHz
RF	
Frequency Range	72.0250-75.9500 MHz & 216.0125-216.9875 MHz
Physical	
Material	Polyethylene Insulation, PVC Jacket, tinned copper conductor, tinned copper braided shield
Shipping Weight	4 lbs. (1.81 kg) per 100 ft.
Diameter	Outer: .192 in. (4.88 mm), Inner: .116 in. (2.95 mm)
Unit Weight	3.5 lbs. (1.6 0 kg) per 100 ft.