



Configuration:

LP-IL-1 Hearing Loop Receiver with Lanyard Package

Product Overview:

The LP-IL-1 is a high quality audio hearing loop receiver which allows a non-hearing aid user to listen to the audio that is being produced by the Hearing Loop system. The receiver also provides a visual as well as auditory confirmation with the included headphone and ear pieces allowing for facility managers and system installers to check system performance.

Highlights:

- This complete loop receiver package comes with the Listen Loop receiver, 9V battery and a variety of headphone and ear piece options with replacement cushions
- Allows the user without a hearing aid to listen to hearing loop system using a pair of headphones.
- Essential for installers, venue managers and even organizers to check the induction loop system is working

Includes:

- One (1) Hearing Loop Receiver with Lanyard
- One (1) LA-366 High Capacity 9V Alkaline Battery for LR-IL-1
- One (1) LA-161 Single Ear Bud
- One (1) LA-164 Ear Speaker
- One (1) LA-165 Stereo Headphones
- One (1) LA-405 Universal Stereo Ear Buds
- One (1) LA-163 Replacement Cushions for Ear Buds (20)
- One (1) LA-167 Replacement Cushions for Stereo Headphones (10)
- One (1) User's Guide

Product Specification: Hearing Loop Receiver with Lanyard Package	
Audio	
Frequency Response	85 Hz - 6 kHz ± 0.5 dB
Distortion	< 0.5% THD @ 1 kHz
Indicators	
Battery Status	OK when LED Illuminated
RF	
Output Power	110 dBA SPL at 16 Ohm Load
Power	
Battery Type	9V Alkaline
Battery Life	Approximately 100 hrs.
Physical	
Width	2.5 in. (63 mm)
Height	4.0 in. (102 mm)
Depth	.87 in. (22 mm)

Product Specification: Hearing Loop Receiver with Lanyard Package	
Shipping Weight	1.2 lbs. (0.6 kg)
Weight	.31 lbs. (.14 kg)