

PMM-60A and PMM-120A

60 or 120 Watt Professional Grade
Public Address Mixer / Amplifier



PMM-120A Shown

Specifications

PMM-60A • 60 WATTS RMS POWER

PMM-120A • 120 WATTS RMS POWER

Both Include:

- 6 Mic Inputs (4 XLR Connectors)
- 70/25 Volt or 4, 8, 16 Ohm Output
- Priority Paging with Auto Mute Function
- Music on Hold Line Level Out w/ Level Control
- 600 Ohm Telephone Paging Input
- Master Volume Control
- Separate Bass & Treble Control on Output Stage
- 2 Auto Summing Stereo to Mono Aux Inputs
- Accessory AC Outlet

Specifications subject to change.

