

**NPB
560A**

Switchcraft® EH Series Audio/Video/Data



EHHD15FFB



EHUSBAB



EHUSBBAB



EHFW2



EHFWX2B



EHDB9FF

The EH Series by Switchcraft® is a complete line of audio, video, and data connectors built into standard panel-mount XLR housings. Custom combinations of EH Series connectors can be quickly and easily loaded into an empty 19-inch 1RU (1x16), 1.5RU (1x16), or 2RU (2x16) rack pre-punched with tapped 4-40 holes.

Switchcraft's EH Series is the fastest and most versatile way to create a custom panel or wall plate perfectly suited to meet the needs of any studio, broadcast facility, or systems integrator.

For more information, visit:
<http://www.switchcraft.com/products/560.html>

Switchcraft®
www.switchcraft.com
5555 N. Elston Avenue/Chicago, IL 60630
Phone: 773-792-2700 Fax: 773-792-2129



EHSVHS2B



EH6MD2

EHBNC2B



EH35MMSSC



EHRCA2B



EH Series	1	2	3	4	5	6
Connector Description	Housing	Connector	Feedthru	Solder	Black Finish	Bagged with Mounting Screws
3.5MM Mono	EH	35MMM	N/A	SC	B	PKG
3.5MM Stereo	EH	35MMS	N/A	SC	B	PKG
SVHS	EH	SVHS	2	N/A	B	PKG
PS/2	EH	6MD	2	N/A	B	PKG
Firewire (EEE1394) Straight-Wired	EH	FW	2	N/A	B	PKG
Firewire (EEE1394) Cross-Wired	EH	FWX	2	N/A	B	PKG
RCA	EH	RCA	2	N/A	B	PKG
BNC	EH	BNC	2	SC	B	PKG
BNC (Recessed Front)	EH	BNC2R	---	N/A	B	PKG
BNC to RCA	EH	BNCRCA	---	---	B	PKG
RCA to BNC	EH	RCABNC	---	---	B	PKG
USB A to B	EH	USBAB	---	---	B	PKG
USB B to A	EH	USBBA	---	---	B	PKG
9-Pin DSUB Male to Male	EH	DB9MM	---	---	B	PKG
9-Pin DSUB Male to Female	EH	DB9MF	---	---	B	PKG
9-Pin DSUB Female to Female	EH	DB9FF	---	---	B	PKG
15-Pin HD DSUB Male to Male	EH	HD15MM	---	---	B	PKG
15-Pin HD DSUB Male to Female	EH	HD15MF	---	---	B	PKG
15-Pin HD DSUB Female to Female	EH	HD15FF	---	---	B	PKG

*Sample Part Number: EHBNC2PKG (BNC Feedthru, Black Housing, Bagged with 4-40 Screws)

*Male to female 9-Pin and 15-Pin DSUBS are user reversible to create female to male connectors.

*All Switchcraft EH Series connectors are fully compatible with blank QG Panels.

Series	Pins	Gender	Fas-Disconnect Option	Termination Style	Finish	Mounting Hole Options
E	3-5 Pins	M=Male F=Female	D=Fas-Disconnect Blank=Standard Locking	ST=Straight PC Terminals RA=Right Angle PC Terminals SC=Solder Cups Blank=Conical Springs (3-Pin Only)	B=Black Blank=Nickel	M3=M3x0.5 Thread 440=#4-40 Thread Blank=Counter-Sunk Hole



E3MSC



E3FSCB



E112BL

Connector Type	Part Number (Nickel Finish)	Part Number (Black Finish)
1/4" Mono Locking Jack	E111L	E111BL
1/4" Stereo Locking Jack	E112BL	E112BLB

*For more information, go to:
<http://www.switchcraft.com/products/560.html>