

The new XTR39 Color LCD touchscreen remote control from Xantech is the perfect solution to the clutter of difficult-to-use remote controls that accompany most home theater systems.

The XTR39 is a stylish, simple-to-use remote control that can be personalized via its vivid full color 3.9" touchscreen display: button layout can be customized; easily identified icons created for virtually any function or command; and multiple screen pages allow less frequently used buttons to be concealed.

Pick it up, and the XTR39 comes to life. Dedicated buttons for the most frequently used buttons such as

volume, channel, power, and mute are perfectly positioned. A convenient touchwheel control sets the XTR39 apart, allowing quick scrolling through menus and commands.

All screen buttons and icons can be programmed to perform multiple commands with a single touch. Additionally, the XTR39 can be configured to control nearly any major system in the home such as A/V system, lighting, climate control, and more.

The XTR39 can be programmed with the same functions and screen appearance as all other Xantech SPLCD SmartPad LCD $^{\text{TM}}$ in-wall touchpanels installed in the home, for consistency and simple operation.

FEATURES

- Vivid 3.9" Color LCD touchscreen display
- · Fully customizable screen graphics and functions
- Capable of controlling virtually every major home system
- · Hard buttons for frequently used commands
- Four easy access programmable macro buttons
- Touchwheel control for quick scrolling through menus and commands

- Eight megabyte internal memory
- RF capable remote
- Long-life rechargeable Lithium-lon battery with battery status indicator and charging stand
- Programmed via Xantech's Universal Dragon
 Drop-IR™ programming software
- Uses same graphics and commands as SPLCD SmartPad LCD™ touchpanels.



XANTECH SYSTEM

The XTR39 is part of the comprehensive Xantech system of products that include multi-room A/V distribution and control, in-wall LCD touchpanel controllers, and source components. The XTR39 designed to work seamlessly with the complete Xantech line, and Universal Dragon Drop-IR™ programming software makes it simple to add a convenient LCD touchscreen remote control to a system that performs identically to the wall-mounted LCD touchpanels in the room.

PROGRAMMING

Xantech's new Universal Dragon Drop-IR™ programming software makes it simple to set-up the XTR39 with the same backgrounds, icons, graphics and commands as all other Xantech Commercial SmartPad LCD™ in-wall touchpanels installed in the job. Users will appreciate the consistent look and feel between the XTR39 and Xantech touchpanels. When it's time to update the system, Universal Dragon saves time and effort.

Specifications:

• Processor: ARM7 Microcontroller

• Processor Speed: 50 MHZ

Memory Size

Random Access Memory: 8 MB

Flash Memory: 8 MB

• LCD

Colors: 256

Size: 3.9" Diagonal

Number of Pixels: 76,800

Orientation: Portrait (240 x 320)

• Touch Screen: Resistive Touch

• Buttons: 11 Touch Positions

• Rotary Wheel: 4 Touch Positions

Battery Type: Lithium Ion Polymer

· Unit Battery Life

Standby on Full Charge: 6 Days Normal Daily Operation: 2.5 Days*

Charge Time: 3.5 Hours

Delivery Condition: ~80% charged

• RF capable remote (2.4GHz. IEEE 802.15.4)

• Cradle Interface Connector: Molded 8-Pin

RF Direct Range: 50' to 100'

• RF Frequency: 2.4 GHz

• IR Range: 30'

• IR Learn Capability: Yes

• IR Library: Yes

• Unit Size: 6.5" x 3.5" x 1.1"

• Unit Weight: 10oz (0.28kg)

Unit Color: Black

• Programmable: Universal Dragon

• Programming Interface: USB 1.1

· Lead Free Unit

Cradle Specifications

Unit Size: 4.5" x 3.75" x 1.25"

Unit Weight: 5oz (0.14kg)

Unit Color: Black

Power Requirements:5 Volts DC @ 2.5A Unit Interface Connector: Molded 8-Pin





REAR VIEW